



Description: Partial Loop disc from multiline acct - includes disc of BTN*Requires RPON

Field	Data Description	Field Entry
RPON #1 Disconnect Circuits including BTN ***Digital Loop Only***		
LSR Form		
CCNA	Customer Carrier Name Abbreviation	<ZTK>
PON	Purchase Order Number	<Your PON>
VER	Version	<01>
LOCQTY	Location Quantity	<001>
DDD	Desired Date Due	<20160612>
REQTYP	Request Type	AB
SLI	Sub Loop Indicator	S
ACT	Activity	C
AGAUTH	Agency Authorization Status	Y
ACTL	Access Customer Terminal Location	<CLEC CLLI>
LSO	Local Serving Office	<562325>
TOS	Type of Service	<12F1> (See Footnote 1)
NC	Network Channel Code	LX-- (See Footnote 2)
NCI	Network Channel Interface Code	02QC2.OOF (See Footnote 2)
NOR	Number of Requests	0102 (See Footnote 4)
RPON	Related Pon	sample1 (See Footnote 4)
RPVER	Related Pon Version	01 (See Footnote 4)
INIT	Initiator Name	<Initiator Name>
TEL NO	Initiator Telephone Number	<9192257998>
EU Form		
LOCNUM	Location Number	<001>
NAME	End User Name	<Our Business Rules>
AFT	Address Format Type	<N if normal, C if assigned house number>
SANO	Service Address Number	<14917>
SASN	Service Address Street Name	<Musketeer>
SATH	Service Address Street Type	<RD>
CITY	City	<Anytown>
STATE	State/Province	<CA>
ZIP	Zip/Postal Code	<12345>
EATN	Existing Account Telephone Number	<2090619999>
LCON	Local Contact	<Jane Doe>
TEL NO	Local Contact Telephone Number	<5623259999>
LS Form		
Administrative		
LQTY	Loop Quantity	<1>
Service Detail (SD1)		
LOCNUM	Location Number	<001>
LNUM	Line Number	<00001>
LNA	Line Activity	D
ECCKT	Exchange Company Circuit ID	11/ARSU/111111/ /GTEW
SYSID	System Identification	<> (See Footnote 3)
Chanpair	Channel Pair	<> (See Footnote 3)



LSR Order Samples

Partial Loop Disconnect

Including BTN

REQTYP: AB

RPON# 1 = ACT: C

RPON# 2 = ACT: N

Description: Partial Loop disc from multiline acct - includes disc of BTN*Requires RPON

Field	Data Description	Field Entry
SHELF	Shelf	<ABC017> (See Footnote 3)
SLOT	Slot	<010> (See Footnote 3)

Description: Partial Loop disc from multiline acct - includes disc of BTN*Requires RPON

Field	Data Description	Field Entry
RPON #2 assignment of new BTN circuit ***Digital Loop Only***		
LSR Form		
CCNA	Customer Carrier Name Abbreviation	<ZTK>
PON	Purchase Order Number	<Your PON>
VER	Version	<00>
LOCQTY	Location Quantity	<001>
DDD	Desired Date Due	<20160612>
REQTYP	Request Type	AB
SLI	Sub Loop Indicator	S
ACT	Activity	N
AGAUTH	Agency Authorization Status	Y
ACTL	Access Customer Terminal Location	<CLEC CLLI>
LSO	Local Serving Office	<562325>
TOS	Type of Service	<12F1> (See Footnote 1)
NC	Network Channel Code	LX-- (See Footnote 2)
NCI	Network Channel Interface Code	02QC2.OOF (See Footnote 2)
NOR	Number of Requests	0202 (See Footnote 4)
RPON	Related Pon	sample1 (See Footnote 4)
RPVER	Related Pon Version	01 (See Footnote 4)
INIT	Initiator Name	<Initiator Name>
TEL NO	Initiator Telephone Number	<9192257998>
IMPCON	Implementation Contact	<Mary Williams>
TEL NO	Telephone Number	<8134383000>
REMARKS	Remarks for RPON#2 Order	Not a New Install - New BTN Change Only
EU Form		
LOCNUM	Location Number	<001>
NAME	End User Name	<Our Business Rules>
AFT	Address Format Type	<N if normal, C if assigned house number>
SANO	Service Address Number	<14917>
SASN	Service Address Street Name	<Musketeer>
SATH	Service Address Street Type	<RD>
CITY	City	<Anytown>
STATE	State/Province	<CA>
ZIP	Zip/Postal Code	<12345>
LCON	Local Contact	<Jane Doe>
TEL NO	Local Contact Telephone Number	<5623259999>
LS Form		
Administrative		
LOTY	Loop Quantity	<2>
Service Detail (SD1)		
LOCNUM	Location Number	<001>
LNUM	Line Number	<00001>
LNA	Line Activity	N



Description: Partial Loop disc from multiline acct - includes disc of BTN*Requires RPON

Field	Data Description	Field Entry
CKR	Circuit Reference	2090611111 (See Footnote 5)
ECCKT	Exchange Company Circuit ID	11/ARSU/111112/ /GTEW (See Footnote 5)
SYSID	System Identification	<> (See Footnote 3)
Chanpair	Channel Pair	<> (See Footnote 3)
SHELF	Shelf	<ABC018> (See Footnote 3)
SLOT	Slot	<010> (See Footnote 3)
Service Detail (SD2)		
LOCNUM	Location Number	<001>
LNUM	Line Number	<00001>
LNA	Line Activity	N
CKR	Circuit Reference	2090611112 (See Footnote 5)
ECCKT	Exchange Company Circuit ID	11/ARSU/111113/ /GTEW (See Footnote 5)
SYSID	System Identification	<> (See Footnote 3)
Chanpair	Channel Pair	<> (See Footnote 3)
SHELF	Shelf	<ABC019> (See Footnote 3)
SLOT	Slot	<010> (See Footnote 3)
Footnotes:		
1. Use appropriate codes - Reference LSR Type of Service Codes		
2. Use appropriate codes - Reference NC/NCI Matrix		
3. Use the Business Rules to populate the appropriate fields for providing CFA		
4. Use the Business Rules to populate the appropriate fields for creating an RPON relationship		
5. The ECCKT and Circuit Reference (CKR) (FICT TNs) should be provided to ensure proper rearrangement for billing		
*Frontier Communications provides LSR Order Samples as a convenience to its CLEC customers. LSR Order Samples (including without limitation any error or inaccuracy contained therein) shall not be deemed to impose any obligation upon Frontier Communications, or to alter any rights or obligations of Frontier Communications or a customer under a valid tariff or agreement.		

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.