



# Switched Access - Establish New SS7 Link

## REQTYP L, ACT N

### VFO Product CCS Links

Revised: 05/24/2021

## 001 - Access Service Request (ASR)

### Administrative Section

Field	Description	Example
CCNA	Customer Carrier Name Abbreviation	XXX (Identifies the IAC Code of the Carrier)
PON	Purchase Order Number	alpha/numeric <b>Note:</b> This Field is Controlled by Customer
VER	Version Identification	alpha/numeric <b>Note:</b> This Field is Controlled by Customer
ICSC	Interexchange Customer Service Center	See Valid ICSC Entries <a href="https://wholesale.frontier.com/-/media/WholesaleDocs/icsc-job-aid.ashx">https://wholesale.frontier.com/-/media/WholesaleDocs/icsc-job-aid.ashx</a>
D/TSENT	Date and Time Sent	mmddy and hour, minute & AM or PM
DDD	Desired Due Date	mmddy
PROJECT	Project Identification	name to be used for all ASRs in the pair or quad
REQTYP	Requisition Type and Status	LD
ACT	Activity	N
LATA	Local Access Transport Area	numeric
RTR	Response Type Requested	alpha/numeric
AFO	Additional Forms	required if QTY greater than 1 and additional circuit detail screens necessary
CUST	Customer Name	optional
UNIT	Unit Identification	C
PIU	Percentage of Interstate Usage	numeric
LTP	Local Transport	may be blank, may be populated with N, or may be populated with RF
CKR	Customer Circuit Reference	alpha/numeric
QTY	Quantity	number of layers being installed
BAN	Billing Account Number	may be blank, may be populated with N, or may be populated with existing Link BAN
ACTL	Access Customer Terminal Location	Link ACTL CLLI
RPON	Related Purchase Order Number	PON of other Link in pair or quad
REMARKS	Remarks	what the Links will be used for, other customers involved in the pair or quad, any additional PONs not populated in RPON field

## Bill Information

Field	Description	Example
<b>BILLNM</b>	Billing Name	Bill name for ACNA
<b>SBILLNM</b>	Secondary Billing Name	optional
<b>ACNA</b>	Access Customer Name Abbreviation	alpha
<b>STREET (Bill)</b>	Street Address (BILL)	# and street name assigned by US Postal Service
<b>FLOOR (Bill)</b>	Floor (BILL)	optional
<b>ROOM (Bill)</b>	Room (BILL)	optional
<b>CITY (Bill)</b>	City (BILL)	city name for street address
<b>STATE (Bill)</b>	State/Province (BILL)	alpha
<b>ZIP CODE (Bill)</b>	Zip Code (BILL)	numeric
<b>BILLCON</b>	Billing Contact	employee from ACNA that can be contacted for billing issues
<b>TEL NO (Bill)</b>	Telephone Number (BILL)	numeric

## Contact Information

Field	Description	Example
<b>INIT</b>	Initiator	customer's employee submitting ASR
<b>TEL NO (INIT)</b>	Telephone Number (Initiator)	numeric
<b>INIT FAX NO</b>	Initiator Facsimile Number	optional
<b>INIT EMAIL</b>	Initiator Electronic Mail Address	optional
<b>DSGCON</b>	Design/Engineering Contact	name of customer's designer
<b>TEL NO (DSG CON)</b>	Telephone Number (Design Contact)	numeric
<b>DSG FAX NO</b>	Design Facsimile Number	optional
<b>STREET (DSG CON)</b>	Street Address (Design Contact)	designer's mailing address street
<b>FLOOR (DSG CON)</b>	Floor (Design Contact)	optional
<b>ROOM (DSG CON)</b>	Room (Design Contact)	optional
<b>CITY (DSG CON)</b>	City (Design Contact)	designer's mailing address city
<b>STATE (DSG CON)</b>	State/Province (Design Contact)	alpha
<b>DSG EMAIL</b>	Design Electronic Mail Address	optional
<b>IMP CON</b>	Implementation Contact	customer's testing contact
<b>TEL NO (IMP CON)</b>	Telephone Number (Implementation Contact)	numeric



## 004 - Trunking Service Detail

Field	Description	Example
NC	Network Channel Code	See following Note: <b>Note:</b> Customers must refer to iconectiv for accurate NC/NCI/SECNCI combinations <b>or</b> refer to the NC/NCI/SECNCI job aid found at <a href="https://wholesale.frontier.com/access-services/switched-access-ordering">https://wholesale.frontier.com/access-services/switched-access-ordering</a>
NCI	Network Channel Interface Code	See NC Note Above
QACI	Quantity Additional Circuit Information	numeric, if necessary
CFA	Connecting Facility Assignment	ID of highest facility
CSL	Customer Switch Location	alpha/numeric CLLI of distant point
CST	Customer Switch Type	type of switch at distant point
CSPC	Customer Signaling Point Code	numeric
SCFA	Secondary Connecting Facility Assignment	DS1 ID if CFA is populated
SECLOC	Secondary Location	STP CLLI

## Service Signaling Point Codes

Field	Description	Example
LT	Link Type	alpha
SLC	Signaling Link Code	numeric



### Change Log:

Date	Revision
8/21/2015	Updated to add CTF (California, Texas and Florida) ICSC codes of GT10 and GT11 effective 4-1-2016
05/24/2021	Update embedded URLs

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.