



# **Version 9.30.28 PS FORM**

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

© 2024 Frontier Communications Parent, Inc. All rights reserved.



**Contents**

Section: ADMINISTRATIVE ..... 4

    PQTY - Port Quantity..... 4

Section: SERVICE DETAIL ..... 4

    LOCNUM - Location Number ..... 4

    LNUM - Line Number..... 4

    NPI - Number Portability Indicator ..... 4

    LNA - Line Activity ..... 5

    LTOS - Line Type of Service ..... 7

    TNS - Telephone Numbers ..... 9

    TERS - Terminal Numbers ..... 11

    OTN - Out Telephone Number ..... 11

    EXKEY - Exchange Key ..... 11

    FPI - Freeze PIC Indicator..... 11

    PIC - InterLATA Presubscription Indicator Code..... 12

    LPIC - IntraLATA Presubscription Indicator Code..... 12

    TSP - Telecommunications Service Priority ..... 13

    SAN - Subscriber Authorization Number..... 13

    CKR - Customer Circuit Reference ..... 14

    ECCKT - Exchange Company Circuit ID..... 14

    RL - Reuse Loop ..... 15

    RECKT - Related Exchange Company Circuit ..... 15

    VPID ~ Virtual Path Indicator..... 15

    VPI ~ Virtual Path Identifier ..... 15

    VCI ~ Virtual Circuit Identifier ..... 15

    VPID2 ~ Virtual Path Indicator 2..... 15

    VPI2 ~ Virtual Path Identifier 2 ..... 16

    VCI2 ~ Virtual Circuit Identifier 2 ..... 16

    UDSPEED ~ Upstream and Downstream Speed..... 16

    CBCID ~ Cross Box Cable Identification ..... 16

    CBP1 ~ Cross Box Pair 1 ..... 16

    OECCKT – Out Exchange Company Circuit ID ..... 16



TC OPT - Transfer of Call Options ..... 17

TC TO PRI - Transfer of Calls To Primary Number ..... 17

TC TO SEC - Transfer of Calls To Secondary Number ..... 17

TCID - Transfer of Calls To Identifier ..... 18

TC NAME - Transfer of Calls To Name..... 18

TCID 2 - Transfer of Calls To Identifier 2 ..... 18

TCNAME 2 - Transfer of Calls To Name 2..... 18

TC PER - Transfer of Calls Period ..... 19

SDP - Shared Data Provider ..... 19

LOOPQUAL - Loop Qualification Status ..... 20

ISR - Installation Service Requested..... 20

NIDR - NID Request..... 21

IWJK - Inside Wire Jack Code..... 21

IWJQ - Inside Wire Jack Quantity ..... 21

SYSTEM ID - System Identification..... 22

SHELF - Shelf..... 22

SLOT - Slot..... 22

RELAY RACK - Relay Rack ..... 23

CHAN/PAIR - Channel/Pair..... 23

CFA - Connecting Facility Assignment..... 24

SSIG - Start Signaling ..... 24

BA - Blocking Activity..... 24

BLOCK - Block ..... 25

ODP – Office Dialing Plan ..... 25

FA - Feature Activity ..... 26

FEATURE - Feature Codes..... 26

FEATQTY - Feature Quantity ..... 27

FEATURE DETAIL - Feature Detail ..... 27

APPENDIX A: ERROR MESSAGE TABLE ..... 28

APPENDIX B - CHANGE CONTROL LOG ..... 34



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
<b>Section: ADMINISTRATIVE</b>							
001	PON					<b>FRONTIER DOES NOT SUPPORT</b>	P
002	VER					<b>FRONTIER DOES NOT SUPPORT</b>	P
003	AN					<b>FRONTIER DOES NOT SUPPORT</b>	P
004	ATN					<b>FRONTIER DOES NOT SUPPORT</b>	P
005	PQTY - Port Quantity	Identifies the quantity of ports involved in this service request	N	1-5		1. If not populated, then return error: FTRPS001 PQTY IS REQUIRED  2. If populated and (dl > 5 or dc not numeric), then return error: FTRPS002 PQTY VALID VALUE = 1-5 NUMERIC  3. If populated and vv not = 1 and ((SDP = C, E, F, G) or (LNA = C and SDP = D)), then return error: FTRPS003 PQTY VALID VALUE MUST EQUAL 1	R
006	ORD					<b>FRONTIER DOES NOT SUPPORT</b>	P
007	PG_of_					<b>FRONTIER DOES NOT SUPPORT</b>	P
<b>Section: SERVICE DETAIL</b>							
008	LOCNUM - Location Number	Identifies this service location number for the service requested.	N	1-3		1. If not populated, then return error: FTRPS004 LOCNUM IS REQUIRED  2. If populated and (dl > 3 or dc not numeric), then return error: FTRPS005 LOCNUM VALID VALUE = 1-3 NUMERIC	R
009	LNUM - Line Number	Identifies the first line or trunk as a unique number and each additional line or trunk segment as a unique number	N	1-5		1. If not populated, then return error: FTRPS006 LNUM IS REQUIRED  2. If populated and (dl > 5 or dc not numeric), then return error: FTRPS007 LNUM VALID VALUE = 1-5 NUMERIC  <b>Note:</b> 1.Once LNUM is generated it cannot be changed and is retained through completion of the request 2.The values are to be assigned consecutively and must be unique throughout the request at the LOCNUM field level	R
010	NPI - Number Portability Indicator	Identifies the status of the telephone number being ported	A	1-1	C= Port in working TN, E= Port in wireless TN, F=Not applicable	1. If not populated and LSR.NPDI = B, D, then return error: FTRPS008 NPI IS REQUIRED  2. If populated and LSR.NPDI not = B, D, then return error: FTRPS009 NPI IS PROHIBITED  3. If populated and vv not = C, F and LSR.NPDI = D, then return error: FTRPS010 NPI VALID VALUE = C, F WHEN NPDI = D	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						4. If populated and vv not = E, F and LSR.NPDI = B, then return error: FTRPS011 NPI VALID VALUE = E, F WHEN NPDI = B	
011	LNA - Line Activity	Identifies the activity involved at the line level.	A	1-1	C= Change an existing account, e.g., rearrangement, partial disconnect or addition, D=Disconnection, B=Restore S=Seasonal (vacation) Suspend N= New installation and/or account, P=PIC change, T=Outside move, V= Conversion of service to new LSP as specified, X=Telephone number change, Z=Restructure	1. If populated and vv = C and HGI form not populated and ((FPI, PIC, LPIC, OTN, BLOCK, TSP, IWJK, FA, NIDR are not populated) and (SDP not = D)), then return error: FTRPS012 WHEN LNA IS C AT LEAST ONE OF THE FIELDS FPI, PIC, LPIC, OTN, BLOCK, TSP, IWJK, FA, NIDR MUST BE POPULATED OR SDP = D 2.If populated and vv does not = N, T and position 1 of LSR.REQTYP = D and LSR.ACT = T, and the NPANXX is Frontier 13 or EU.STATE=CT then return error: FTRPS013 LNA VALID VALUE = N, T WHEN ACT = T 3. If populated and vv not = N and position 1 of LSR.REQTYP = D and LSR.ACT = C and any occurrence of SDP = A, then return error: FTRPS014 LNA VALID VALUE = N WHEN ACT = C AND SDP = A 4. If populated and all occurrences of vv not = V and position 1 of LSR.REQTYP = D and LSR.ACT = V and position 2 of LTOS = P, then return error: FTRPS015 ALL OCCURRENCES OF LNA MUST = V FOR ACT/LTOS COMBINATION 5.If populated and vv does not = N, V, D and LSR.REQTYP = DB, and LSR.ACT=V and position 2 of LTOS does not = P, return error FTRPS016 LNA VALID VALUE = N, V, D 6. If populated and vv not = C, N, D, P, T, X, Z and position 1 of LSR.REQTYP = D and LSR.ACT = C and position 2 of LSR.TOS not = Y, then return error: FTRPS017 LNA VALID VALUE = C, N, D, P, T, X, Z 7. If populated and vv not = B and position 1 of LSR.REQTYP = D, F and LSR.ACT = B and position 2 of LSR.TOS not = Y, then return error: FTRPS019 LNA VALID VALUE = B WHEN ACT = B 8. If populated and vv not = S and position 1 of LSR.REQTYP = D, F and LSR.ACT = S and position 2 of LSR.TOS not = Y, then return error: FTRPS020 LNA VALID VALUE = S WHEN ACT = S	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>9. If populated and vv not = N and LSR.ACT = N and position 2 of LSR.TOS not = Y, then return error: FTRPS022 LNA VALID VALUE = N WHEN ACT = N</p> <p>10. If populated and one occurrence of vv = T and any other occurrences of vv not = T, D and LSR.ACT = C, then return error: FTRPS023 LNA VALID VALUE = T, N WHEN ONE OCCURRENCE = T AND ACT = C</p> <p>11. If populated and vv not = V and LSR.ACT = V and RL is populated, then return error: FTRPS024 LNA VALID VALUE = V WHEN ACT = V</p> <p>12. If populated and vv = T and LSR.ACT = B, D, N, S, V, then return error: FTRPS025 LNA VALID VALUE = T IS PROHIBITED FOR ACTIVITY</p> <p>13. If populated and vv = Z and (LSR.ACT not = C or LSR.AC not = A), then return error: FTRPS026 LNA VALID VALUE = Z ONLY WHEN ACT = C AND AC = A</p> <p>14. If populated and position 2 of LSR.TOS = Y, then return error: FTRPS027 LNA IS PROHIBITED</p> <p>15. If not populated and position 2 of LSR.TOS not = Y, then return error: FTRPS028 LNA IS REQUIRED</p> <p>16. If populated and vv does not = B, C, D, N, P, S, T, V, X, Z, then return error: FTRPS029 LNA VALID VALUE = B, C, D, N, P, S, T, V, X, Z</p> <p>17. If populated and vv not = C, N, D, P, X and position 1 of LSR.REQTYP = F and LSR.ACT = C and position 2 LSR.TOS not = Y, then return error: FTRPS184 LNA VALID VALUE = C, N, D, P, X</p> <p>18. If populated and vv not = N, V, D and position 1 of LSR.REQTYP = F and LSR.ACT = V and position 2 of LSR.TOS not = Y, then return error: FTRPS185 LNA VALID VALUE = N, V, D</p>	



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>19.If populated and vv does not = D,T and DDDO is populated, return error FTRPS055 LNA VALID VALUE = D, T WHEN DDDO IS POPULATED</p> <p>20.If populated and vv = S and position 2 of LSR.TOS or position 2 of LTOS =P, return error FTRPS091 LNA CANNOT = S WHEN LSR.TOS OR PS.LTOS =P</p> <p>21.If populated vv = N, D and LSR.REQTYP=DB, LSR.ACT=V and position 2 of LSR.TOS=C, return error FTRPS150 LNA CANNOT = N,D WHEN REQTYP=DB, ACT=V AND POSITION 2 OF TOS=C</p> <p>22.If populated and vv=D and LSR.REQTYP=DB, LSR.ACT=V and position 2 of LSR.TOS=P, return error FTRPS152 LNA CANNOT = D WHEN REQTYP=DB, ACT=V AND POSITION 2 OF LSR.TOS=P</p> <p>23.If vv not = N and LSR.ACT = N, T, and NPANXX is Not Frontier 13 or EU.STATE not = CT then return error: FTRPS141 LNA VALID VALUE = N WHEN ACT = N, T</p> <p>24.If populated and vv does not = C, D, N, X and LSR.ACT = M, then return error FTRPS034 LNA VALID VALUE = C, D, N, X WHEN ACT = M</p> <p>25.If populated and vv does not = S and LSR.ACT = S, then return error FTRPS148 LNA MUST = S WHEN ACT = S</p> <p><b>Note:</b> On multiple line accounts, if the entire account is not being suspended or restored from seasonal service then a service specific form (PS) is required. The LSR ACT = S (Suspend) or B (Restore) and PS LNA = S or B for each TNS being suspended or restored.</p>	
012	NOTYP					<b>FRONTIER DOES NOT SUPPORT</b>	P
013	LTOS - Line Type of Service	Identifies the type of service at the line level.	AN Hyphen	4-4	<p><b>Acquired WV</b>  <b>1st character:</b>            Hyphen(-)=Not Applicable  <b>2nd character:</b>            D=Advanced Services            P=Data Voice Split Line            Hyphen(-)=Not applicable            1=Analog Line Port (non-Centrex)            2=Analog Line Port (Centrex)            3=Electronic Key Port (Centrex)</p>	<p>1. If populated and position 2 of vv not = P and SDP = A, B and NPA NXX is not Frontier 13 and position 3 of LSR.TOS does not = B and position 4 of LSR.TOS does not = L, then return error: FTRPS030 LTOS POSITION 2 INVALID</p> <p>2. If populated and position 2 of vv not = (-)Hyphen, D, P, L, 1 and position 1 of LSR.TOS = 2 and NPA NXX is Acquired WV, then return error: FTRPS031 LTOS POSITION 2 VALID VALUE = (-)HYPHEN,D, P, L, 1 WHEN POSITION 1 OF TOS = 2</p>	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P	
					<p>4=P Phone Equivalent Port  5=DS1 DID/DOD/PBX  6=TR008 Port  <b>3<sup>rd</sup> character:</b>  B=Wholesale Broadband  Hyphen (-)=Not Applicable  <b>4<sup>th</sup> character:</b>  L=Broadband Lineshare  R=RCF  S=Standalone Broadband  V=VoIP  Hyphen (-)=Not Applicable</p> <p><b>Frontier 13 / CT</b>  For information on available LTOS values in F13 or CT, please see Valid Values for LSR.TOS field</p> <p><b>Legacy</b>  <b>1st character:</b>  1=Business  2=Residence  <b>2nd character:</b>  A=Hunting  B=Single Line or Multi Line without Hunting  <b>3<sup>rd</sup> character:</b>  B=Wholesale Broadband  F=Flat Rate  P=Wholesale Platform Voice  <b>4<sup>th</sup> character:</b>  L=Broadband Lineshare  R=RCF  S=Standalone Broadband  V=VoIP  Hyphen (-)=Not Applicable</p>		<p>3. If populated and vv not = -1-R or -D-R and position 4 of LSR.TOS = R and NPA NXX is Acquired WV, then return error: FTRPS035 LTOS VALID VALUE = -1-R OR -D-R WHEN POSITION 4 OF TOS = R</p> <p>4. If populated and position 1 of vv not = hyphen (-)and NPA NXX is Acquired WV, then return error: FTRPS036 LTOS POSITION 1 VALID VALUE = HYPHEN</p> <p>5. If populated and position 2 of vv not = (-)Hyphen,D, L, P, 1, 2, 3, 4, 5, 6 and NPA NXX is Acquired WV, then return error: FTRPS037 LTOS POSITION 2 VALID VALUE = (-)HYPHEN,D, L, P, 1, 2, 3, 4, 5, 6</p> <p>6. If populated and position 3 of vv not = hyphen, B and NPA NXX is Acquired WV, then return error: FTRPS038 LTOS POSITION 3 VALID VALUE = HYPHEN OR B</p> <p>7. If populated and position 4 of vv not = R, hyphen, S, L, V and NPA NXX is not Frontier 13 or EU.STATE not = CT, then return error: FTRPS039 LTOS POSITION 4 VALID VALUE = R, HYPHEN, S, L, V</p> <p>8. If populated and dl not = 4, then return error: FTRPS040 LTOS VALID LENGTH = 4</p> <p>9.If populated and vv of position 2=P and vv of position 3 does not =M and NPA NXX is Frontier 13, return error FTRPS154 LTOS POSITION 3 MUST = M WHEN POSITION 2 = P</p> <p>10.If populated and vv does not = LSR.TOS and NPA NXX is not Acquired WV, return error FTRPS164 LTOS MUST = LSR.TOS</p> <p>11.If populated position 1 vv does not = 1, 2 and NPA NXX is Frontier 13 or Legacy, return error FTRPS220 LTOS POSITION 1 VALID VALUE = 1, 2</p> <p>12.If not populated and LSR.REQTYP=DB, LSR.ACT=N,T,M,V,C and LNA does not = D, return error FTRPS190 LTOS REQUIRED</p>	





Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>13.If populated and vv does not = --BS or --BL and position 3 of LSR.TOS = B and NPA NXX is Acquired WV, return error FTRPS021 LTOS MUST EQUAL --BS OR --BL</p> <p>14.If populated and position 2 of vv does not = A, B and NPA NXX is Legacy, return error FTRPS205 LTOS POSITION 2 INVALID</p> <p>15.If populated and position 3 of vv does not = B, P, F and NPA NXX is Legacy, return error FTRPS222 LTOS POSITION 3 INVALID</p> <p>16.If populated and POS 4 does not = L and POS 4 of LSR.TOS = L, return error FTRPS018 POS 4 PS.LTOS MUST = L WHEN POS 4 LSR.TOS=L</p> <p>17. If populated and POS 4 does not = S and POS 4 of LSR.TOS =S, return error FTRPS033 POS 4 PS.LTOS MUST = S WHEN POS 4 LSR.TOS=S</p> <p>18.If populated and vv does not = ---V position 4 of LSR.TOS = V and NPA NXX is Acquired WV, return error FTRPS225 LTOS MUST EQUAL ---V</p> <p>19. If populated and vv does not = V and position 4 LSR.TOS = V, then return error FTRPS230 POS 4 PS.LTOS MUST = V WHEN POS 4 LSR.TOS=V</p> <p>Note: For information on available LTOS values in F13 or CT, please see Valid Values for LSR.TOS field</p>	
014	SOE					<b>FRONTIER DOES NOT SUPPORT</b>	P
015	TNI					<b>FRONTIER DOES NOT SUPPORT</b>	P
016	TNS - Telephone Numbers	Identifies the telephone number or consecutive range of telephone numbers for this request	AN Hyphen	1, 10, 15	<p>A=Account level change</p> <p>N=New Telephone Number Requested</p> <p>NNNNNNNNNN</p> <p>NNNNNNNNNN-NNNN</p>	<p>1. If populated and vv = A and SDP = D, then return error: FTRPS041 TNS VALID VALUE = A IS PROHIBITED WHEN SDP = D</p> <p>2.If populated and vv = N and ((LNA not = C, N, X) or (position 2 of LSR.TOS not = D, E, J, B and position 4 of LSR.TOS not = F, R,W,S, V) or EU.AAI does not = NEW ADDR, return error: FTRPS042 TNS VALID VALUE = N IS PROHIBITED</p> <p>3. If not populated and position 2 of LSR.TOS not = Y, then return error: FTRPS045 TNS IS REQUIRED</p>	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>4. If populated and position 2 of LSR.TOS = Y, then return error: FTRPS046 TNS IS PROHIBITED</p> <p>5. If populated and dl = 1 and vv not = A, N, then return error: FTRPS047 TNS VALID VALUE = A, N WHEN LENGTH = 1</p> <p>6. If populated and dl = 10, 15 and valid format not = XXXXXXXXXXXX, XXXXXXXXXXXX-XXXX, then return error: FTRPS048 TNS VALID FORMAT = XXXXXXXXXXXX, XXXXXXXXXXXX-XXXX</p> <p>7. If populated and dl not = 1, 10, 15, then return error: FTRPS049 TNS VALID LENGTH = 1, 10, 15</p> <p>8. If vv = A and any other occurrence of TNS = A, then return error: FTRPS196 ONLY ONE TNS VALUE OF A IS ALLOWED</p> <p>9.If populated and LNA=X, and vv is = to vv of OTN, return error FTRPS166 TNS MUST BE DIFFERENT FROM OTN WHEN LNA=X</p> <p>10.If not populated and LSR.REQTYP= DB and LSR.ACT=C,V, return error FTRPS186 TNS REQUIRED WHEN REQTYP=DB AND ACT=C,V</p> <p>11. If populated and ACT = N,V,C and position 2 of LSR.TOS=P and number of occurrences of PS.TNS &gt; 1, return error FTRPS224 LINE SPLIT MUST BE ON STAND ALONE ACCOUNT</p> <p>12.If populated and LSR.ACT = N,V,C and position 2 of LSR.TOS=C and number of occurrences of TNS &gt; 1, and the NPANXX is Frontier 13, return error FTRPS043 COIN OR PAL MUST BE ON STAND ALONE ACCOUNT</p> <p>13.If populated and LSR.ACT = N,V,C and position 4 of LSR.TOS=R and number of occurrences of TNS &gt; 1 and the NPANXX is Frontier 13, return error FTRPS044 RCF MUST BE ON STAND ALONE ACCOUNT</p> <p>14.If populated and vv does not = A, and REQTYP = DB, and ACT = S and EU.STATE = NV, SC, return error FTRPS153 FULL ACCOUNT SUSPENSION REQUIRED</p>	



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>Note:            1)The telephone number or range of telephone numbers populated in the TNS field MUST be valid telephone numbers.            2)For new services, the telephone numbers must be provided by Frontier in response to the Pre-Order Direct TN Reservation (TXTYP=B). Telephone number reservation is required for all non-complex, new services.            3)Populating the field with any invalid telephone numbers is prohibited and the LSR will be rejected.</p>	
017	TERS - Terminal Numbers	Identifies the number for a non-lead line in a multi-line hunt group or consecutive range of terminal numbers	AN , - ; space	1-10		<p>1.If populated and (dl &gt; 10 or dc not = alpha, numeric, hyphen, space, comma, semicolon), then return error: FTRPS050 TERS VALID VALUE = 10 ALPHA, NUMERIC, HYPHEN, SPACE, COMMA, SEMICOLON</p> <p>Note:            1.A pilot (lead) telephone number in the TNS field must accompany this field            2.When this field is populated, the TNS field must not be ranged            3.The first position is reserved for a terminal number indicator</p>	O
018	S					<b>FRONTIER DOES NOT SUPPORT</b>	P
019	OTNI					<b>FRONTIER DOES NOT SUPPORT</b>	P
020	OTN - Out Telephone Number	Identifies the existing telephone number that is being changed	N	10-10		<p>1. If not populated and LNA = X, then return error: FTRPS056 OTN IS REQUIRED</p> <p>2. If populated and LNA does not = C, T, X, then return error: FTRPS057 OTN IS PROHIBITED</p> <p>3. If populated and LNA not = X and SDP = C, D, E, F, G, then return error: FTRPS058 OTN IS PROHIBITED</p> <p>4. If populated and (dl nopt = 10 or dc not = numeric), then return error: FTRPS059 OTN VALID VALUE = 10 NUMERIC</p>	O
020 a	EXKEY - Exchange Key	Identifies the Exchange Key of the new switch	AN	1-6		<p>1. If not populated and NPI = C, E, F, then return error: FTRPS060 EXKEY IS REQUIRED</p> <p>2. If populated and dl &gt; 6, then return error: FTRPS061 EXKEY VALID LENGTH = 1-6</p>	O
021	FPI - Freeze PIC Indicator	Identifies a request that PIC activity on the Working Telephone Number (WTN) be restricted.	A	1-1	A= Freeze IntraLATA PIC B= Freeze Inter & IntraLAT PIC E= Freeze InterLATA PIC R= Remove InterLATA freeze S= Remove IntraLATA freeze T= Remove Inter & IntraLATA freezes	<p>1. If populated and vv = R, S, T and ((LNA = N, T) or (LNA = V and RL is populated)), then return error: FTRPS062 FPI VALID VALUE = R, S, T IS PROHIBITED</p> <p>2. If populated and (LNA = B, D, S, X or position 2 of LSR.TOS = Y), then return error: FTRPS063 FPI IS PROHIBITED</p> <p>3. If populated and SDP = C, D, E, F, G, then return error: FTRPS064 FPI IS PROHIBITED</p>	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						4. If populated and vv not = A, B, E, R, S, T, then return error: FTRPS065 FPI VALID VALUE = A, B, E, R, S, T	
022	PIC - InterLATA Presubscription Indicator Code	Identifies the Pre-subscription Indicator Code (PIC) of the carrier the customer has selected for InterLATA traffic	AN	2-4	None=None NC=No change VOIP= VoIP	<p>1. If populated and vv = NC and LNA = N, T, V, then return error: FTRPS066 PIC VALID VALUE = NC IS PROHIBITED</p> <p>2.If not populated and LNA = N, P, T, V, return error FTRPS067 PIC IS REQUIRED</p> <p>3. If populated and (LNA = B, D, S, X or position 2 of LSR.TOS = Y), then return error: FTRPS068 PIC IS PROHIBITED</p> <p>4. If populated and SDP = C, D, E, F, G, then return error: FTRPS069 PIC IS PROHIBITED</p> <p>5.If populated and vv not = NONE, NC, VOIP and ((dl &lt; 2 or &gt; 4) or (dc not = numeric)), then return error: FTRPS070 PIC VALID VALUE = NONE, NC, VOIP OR 2-4 NUMERIC</p> <p>6.If populated and vv does not = NONE and position 3 of LSR.TOS = B or position 4 of LSR.TOS = S, return error FTRPS191 PIC VALID VALUE = NONE</p> <p>7. If populated and vv = 0000, return error FTRPS223 PIC 0000 INVALID</p> <p>8.If populated and vv does not = VOIP and position 4 of LSR.TOS = V return error FTRPS226 PIC VALID VALUE MUST = VOIP</p> <p>9. If populated and the vv = VOIP and the position 4 of LSR.TOS does not = V return error FTRPS228 PIC VALUE INVALID</p>	O
023	LPIC - IntraLATA Presubscription Indicator Code	Identifies the Pre-subscription Indicator Code (PIC) of the carrier the customer has selected for IntraLATA traffic.	AN	2-4	None=None NC=No change VOIP= VoIP	<p>1. If populated and vv = NC and LNA = N, T, V, then return error: FTRPS071 LPIC VALID VALUE = NC IS PROHIBITED</p> <p>2.If not populated and LNA = N, P, T, V, return error FTRPS072 LPIC IS REQUIRED</p> <p>3. If populated and (LNA = B, D, S, X or position 2 of LSR.TOS = Y), then return error: FTRPS073 LPIC IS PROHIBITED</p> <p>4. If populated and SDP = C, D, E, F, G, then return error: FTRPS074 LPIC IS PROHIBITED</p>	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>5.If populated and vv not = NONE, NC, VOIP and ((dl &lt; 2 or &gt; 4) or (dc not = numeric)), then return error: FTRPS075 LPIC VALID VALUE = NONE, NC, VOIP OR 2-4 NUMERIC</p> <p>6.If populated and vv = 6500 or 5448, return error FTRPS052 INVALID LPIC</p> <p>7.If populated and vv does not = NONE and position 3 of LSR.TOS = B or position 4 of LSR.TOS = S, return error FTRPS192 LPIC VALID VALUE = NONE</p> <p>8.If populated and vv does not = VOIP and position 4 of LSR.TOS = V, return error FTRPS227 LPIC VALID VALUE MUST = VOIP</p> <p>9. If populated and vv = VOIP and position 4 of LSR.TOS does not = V, return error FTRPS229 LPIC VALUE INVALID</p>	
024	IPIC					<b>FRONTIER DOES NOT SUPPORT</b>	P
025	TSP - Telecommunications Service Priority	Indicates the provisioning and restoration priority as defined under the TSP Service Vendor Handbook	AN -	12-12	Format = XXXXXXXX-XX  (Note - X = alpha/numeric)	<p>1. If populated and position 1 of LSR.TOS = 2, then return error: FTRPS076 TSP IS PROHIBITED</p> <p>2. If populated and LNA = P, X, then return error: FTRPS077 TSP IS PROHIBITED</p> <p>3. If populated and valid format not = XXXXXXXX-XX, then return error: FTRPS078 TSP VALID FORMAT = XXXXXXXX-XX</p> <p>4. If populated and position 11 not = E, 0, 1, 2, 3, 4, 5, then return error: FTRPS181 TSP VALID VALUE FOR POSITION 11 MUST = E, 0, 1, 2, 3, 4, 5</p> <p>5. If populated and position 12 not = 0, 1, 2, 3, 4, 5, then return error: FTRPS182 TSP VALID VALUE FOR POSITION 12 MUST = 0, 1, 2, 3, 4, 5</p> <p>Note: 1.These codes are assigned by the TSP Program Office 2.A TSP code ending in "00" indicates "revocation", the removal of a previously assigned TSP code</p>	O
026	SAN - Subscriber	Identifies a number equivalent to	AN	1-30		1.If populated and (dl > 30 or dc not = alpha, numeric, ampersand, apostrophe, asterisk, colon, comma, dollar sign, hyphen, number sign, parentheses, period, quotation marks,	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
	Authorization Number	the end user purchase order number.	& ' * : , \$ - # ( ) . " space			space), then return error: FTRPS079 SAN VALID VALUE = 1-30 ALPHA, NUMERIC, AMPERSAND, APOSTROPHE, ASTERISK, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PARENTHESES, PERIOD, QUOTATION MARKS, SPACE  Note: This may, at the option of the customer, be a requirement when providing service to some governmental agencies.	
027	CKR - Customer Circuit Reference	Identifies the circuit number or sequential range of circuit numbers assigned by the customer	AN & ' * ( ) : , \$ - # % + " ; . Space	1-41		1.If populated and (dl > 41 or dc not = alpha, numeric, ampersand, apostrophe, asterisk, parentheses, colon, comma, dollar sign, hyphen, number sign, percent, plus sign, quote, semicolon, space, period), then return error: FTRPS080 CKR VALID VALUE = 1-41 ALPHA, NUMERIC, AMPERSAND, APOSTROPHE, ASTERISK, PARENTHESES, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PERCENT, PLUS SIGN, QUOTE, SEMICOLON, SPACE, PERIOD  Note: CKR is used by the customer as a cross reference to the provider circuit ID(s) and in many cases to identify the customer's end-to-end service.	O
028	LEAN					<b>FRONTIER DOES NOT SUPPORT</b>	P
029	LEATN					<b>FRONTIER DOES NOT SUPPORT</b>	P
030	ECCKT - Exchange Company Circuit ID	Identifies a provider's circuit identification.	AN /	1-41	TELEPHONE NUMBER FORMAT: NPANXXXXXX  SERIAL NUMBER FORMAT: Prefix/service code and modifier/serial number/suffix code/AP code/segment name (if applicable).	1.If not populated and LSR.ACT=C,D and position 2 of LSR.TOS=Y, return error FTRPS081 ECCKT IS REQUIRED  2. If populated and (dl > 41 or dc not = alpha, numeric, virgule), then return error: FTRPS082 ECCKT VALID VALUE = 1-41 ALPHA, NUMERIC, VIRGULE  Note: 1.May be used to identify multiple circuit IDs 2.The format of the field is defined by the provider 3.All components within the ID should be delimited by virgules 4.The layout of the field is defined by the COMMON LANGUAGE standards 5.When a component of CLT and CLS is purposely omitted, the component should still be delimited and compressed to eliminate any spaces. 6.If all positions in a component of CLT and CLS are not populated, the component should be compressed to eliminate any spaces. 7.Ranges should be shown within the appropriate component of the ID by specifying the lowest value of the component, hyphen, highest value of the component, e.g., trunk numbers 3500 through 3512 would be shown as 3500-3512 8.Use of ranging is based on provider/customer negotiations	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
031	RL - Reuse Loop	Identifies the desire to reuse the loop from an existing service arrangement for this request	A	1-1	Y = Yes	<p>1.If not populated and position 1 of LSR.REQTYP = D and LNA = V and OECKT is populated, then return error: FTRPS083 RL IS REQUIRED</p> <p>2. If populated and ((position 1 of LSR.REQTYP not = D) or (LNA not = V) or (OECKT is not populated)), then return error: FTRPS084 RL IS PROHIBITED</p> <p>3. If populated and vv not = Y, then return error: FTRPS085 RL VALID VALUE = Y</p> <p>Note:            1.This field may be used to notify the NSP-loop of the LSP's desire to reuse the loop(s) for this service request.            2.When this field is populated, no local service request is required from the old LSP/NSP-switch to the NSP-loop for disconnect of the unbundled loop.</p>	O
031 a	RECCKT - Related Exchange Company Circuit	Identifies the provider's related physical circuit ID against which the virtual circuit activity is requested	AN	1-41		<p>1.If populated and dl &gt; 41, return error FTRPS053 RECCKT VALID DATA LENGTH = 1-41</p> <p>Note:            This information will be utilized for the formatting of Wholesale Advantage DSL service on PARTs and RT Overlay</p>	O
031 b	VPID ~ Virtual Path Indicator	Identifies the connection location and quality of service for the virtual path requested	A	1-2		<p>1.If populated and NPA NXX is not Acquired WV, return error FTRPS054 VPID NOT VALID FOR SERVICE TERRITORY</p> <p>Note:            This information will be utilized for the formatting of Wholesale Advantage DSL service on PARTs and RT Overlay</p>	O
031 c	VPI ~ Virtual Path Identifier	Identifies the logical connection address for the virtual path requested	N	1-4		<p>1.If populated and NPA NXX is not Acquired WV, return error FTRPS187 VPI NOT VALID FOR SERVICE TERRITORY</p> <p>Note:            This information will be utilized for the formatting of Wholesale Advantage DSL service on PARTs and RT Overlay</p>	O
031 d	VCI ~ Virtual Circuit Identifier	Identifies the logical address between the provider's switch and the circuit for the virtual circuit requested	N	1-5		<p>1.If populated and NPA NXX is not Acquired WV, return error FTRPS197 VCI NOT VALID FOR SERVICE TERRITORY</p> <p>Note:            This information will be utilized for the formatting of Wholesale Advantage DSL service on PARTs and RT Overlay</p>	O
031 e	VPID2 ~ Virtual	Identifies the logical	A	1-2		<p>1.If populated and NPA NXX is not Acquired WV, return error FTRPS198 VPID2 NOT VALID FOR SERVICE TERRITORY</p>	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
	Path Indicator 2	connection location and quality of service for the virtual path requested				Note: This information will be utilized for the formatting of Wholesale Advantage DSL service on PARTS and RT Overlay	
031f	VPI2 ~ Virtual Path Identifier 2	Identifies the logical connection address between the provider's equipment and the path for the virtual path requested	N	1-4		1.If populated and NPA NXX is not Acquired WV, return error FTRPS199 VPI2 NOT VALID FOR SERVICE TERRITORY  Note: This information will be utilized for the formatting of Wholesale Advantage DSL service on PARTS and RT Overlay	O
031g	VCi2 ~ Virtual Circuit Identifier 2	Identifies the logical connection address between the provider's equipment and the circuit for the virtual circuit requested	N	1-5		1.If populated and NPA NXX is not Acquired WV, return error FTRPS200 VCi2 NOT VALID FOR SERVICE TERRITORY  Note: This information will be utilized for the formatting of Wholesale Advantage DSL service on PARTS and RT Overlay	O
031h	UDSPEED ~ Upstream and Downstream Speed	Identifies the upstream and downstream speed of the virtual circuit.	AN	1-15		1.If populated and NPA NXX is not Acquired WV, return error FTRPS201 UDSPEED NOT VALID FOR SERVICE TERRITORY  Note: This information will be utilized for the formatting of Wholesale Advantage DSL service on PARTS and RT Overlay	O
031i	CBCID ~ Cross Box Cable Identification	Identifies the provider's cable to be connected to the customer's termination in a field location.	AN	1-10		1.If populated and NPA NXX is not Acquired WV, return error FTRPS202 CBCID NOT VALID FOR SERVICE TERRITORY  Note: This information will be utilized for the formatting of Wholesale Advantage DSL service on PARTS and RT Overlay	O
031j	CBP1 ~ Cross Box Pair 1	Identifies the specific pair at the customer's meet point at the cross box located in the field	N	1-4		1.If populated and NPA NXX is not Acquired WV, return error FTRPS203 CBP1 NOT VALID FOR SERVICE TERRITORY  Note: This information will be utilized for the formatting of Wholesale Advantage DSL service on PARTS and RT Overlay	O
032	OECCKT ~ Out Exchange	Identifies the circuit identification that was previously	AN /	1-41	TELEPHONE NUMBER FORMAT: NPNXXXXXX  SERIAL NUMBER FORMAT:	1. If not populated and RL is populated, then return error: FTRPS086 OECCKT IS REQUIRED	O





Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
	Company Circuit ID	provided to the old LSP/NSP-Switch by the NSP-Loop			Prefix/service code and modifier/serial number/suffix code/AP code/segment name (if applicable).	<p>2. If populated and RL is not populated, then return error: FTRPS087 OECCKT IS PROHIBITED</p> <p>3. If populated and (dl &gt; 41 or dc not alpha, numeric, virgule), then return error: FTRPS088 OECCKT VALID VALUE = 1-41 ALPHA, NUMERIC, VIRGULE</p> <p>Note:            1. May be used to identify multiple circuit IDs            2. The format of the field is defined by the provider            3. All components within the ID should be delimited by virgules            4. The layout of the field is defined by the COMMON LANGUAGE standards            5. When a component of CLT and CLS is purposely omitted, the component should still be delimited and compressed to eliminate any spaces.            6. Multiple iterations may apply</p>	
033	TC OPT - Transfer of Call Options	Identifies the type of transfer of call option the end user has requested	A	1	N=None S=Standard T=Split Transfer of Calls	<p>1. If not populated and LNA = D, X, then return error: FTRPS089 TC OPT IS REQUIRED</p> <p>2. If populated and LNA not = S, D, X, then return error: FTRPS090 TC OPT IS PROHIBITED</p> <p>3. If populated and vv does not = N, S, T, return error FTRPS093 TC OPT VALID VALUE = N, S, T</p> <p>4. If populated and vv does not = N and position 3 of LSR.TOS = B or position 4 of LSR.TOS = S, return error FTRPS209 TCOPT VALID VALUE = N</p> <p>5. If populated and vv does not = N and the EU State = TX return error FTRPS032 TC OPT VALID VALUE = N FOR THE STATE OF TX</p>	O
034	TC TO PRI - Transfer of Calls To Primary Number	Identifies the telephone number to which calls are to be referred.	N	10-10		<p>1. If not populated and TC OPT = S, T, return error FTRPS094 TC TO PRI IS REQUIRED</p> <p>2. If populated and TC OPT does not = S, T, return error FTRPS095 TC TO PRI IS PROHIBITED</p> <p>3. If populated and (dl not = 10 or dc not numeric), then return error: FTRPS096 TC TO PRI VALID VALUE = 10 NUMERIC</p>	O
035	TC TO SEC - Transfer of Calls To	Identifies the secondary telephone number to which calls are to be referred	N	10-10		<p>1. If not populated and TC OPT = T, return error FTRPS103 TC TO SEC IS REQUIRED</p> <p>2. If populated and TC OPT does not = T, return error FTRPS104 TC TO SEC IS PROHIBITED</p>	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
	Secondary Number					3. If populated and (dl not = 10 or dc not numeric), then return error: FTRPS105 TC TO SEC VALID VALUE = 10 NUMERIC	
036	TCID - Transfer of Calls To Identifier	Identifies the sequence of telephone numbers and names associated with multiple users of the same TN	N	1-2		1.If not populated and TC OPT = T, return error FTRPS097 TCID IS REQUIRED  2.If populated and TC OPT does not = T, return error FTRPS098 TCID IS PROHIBITED  3. If populated and vv not = 1, then return error: FTRPS099 TCID VALID VALUE FOR INITIAL OCCURRENCE = 1  Note: 1.The TCID should be sequential starting with the number one (1). The first TCID is associated to the TC TO PRI and the first occurrence of the TC NAME fields. 2.The second occurrence of TCID is associated to the first occurrence of the TC TO SEC and the second occurrence of the TC NAME fields. The TCID should incrementally increase by one (1) until all occurrences of TC TO SEC and TC NAME fields have been exhausted.	O
037	TC NAME - Transfer of Calls To Name	Identifies the name or special instructions associated with TC TO to which calls are referred when split of calls is requested	AN , - . space	1-35		1.If not populated and TC OPT = T, return error FTRPS100 TC NAME IS REQUIRED  2.If populated and TC OPT does not = T, return error FTRPS101 TC NAME IS PROHIBITED  3. If populated and (dl > 35 or dc not = alpha, numeric, apostrophe, comma, hyphen, period, space), then return error: FTRPS102 TC NAME VALID VALUE = 1-35 ALPHA, NUMERIC, APOSTROPHE, COMMA, HYPHEN, PERIOD, SPACE	O
037 a	TCID 2 - Transfer of Calls To Identifier 2	Identifies the name(s) associated with TC TO PRI and TC TO SEC fields to which calls are referred when split transfer of calls is requested	N	1-2		1.If not populated and TC OPT = T, return error FTRPS106 TCID 2 IS REQUIRED  2.If populated and TC OPT does not = T, return error FTRPS107 TCID2 IS PROHIBITED  3. If populated and (dl > 2 or dc not numeric), then return error: FTRPS108 TCID 2 VALID VALUE = 1-2 NUMERIC  4. If populated and all occurrences of data are not sequential, then return error: FTRPS183 TCID 2 MUST BE SEQUENTIAL	O
037 b	TCNAME 2 - Transfer of Calls To Name 2	Identifies the names associated with the TC TO SEC field to	AN , - . space	1-35		1.If not populated and TC OPT = T, return error FTRPS109 TCNAME 2 IS REQUIRED	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
		which calls are to be referred when split transfer of calls is requested.				<p>2.If populated and TC OPT does not = T, return error FTRPS110 TCNAME 2 IS PROHIBITED</p> <p>3. If populated and (dl &gt; 35 or dc not alpha, numeric, apostrophe, comma, hyphen, period, space), then return error: FTRPS111 TCNAME 2 VALID VALUE = 1-35 ALPHA, NUMERIC, APOSTROPHE, COMMA, HYPHEN, PERIOD, SPACE</p>	
038	TC PER - Transfer of Calls Period	Indicates the requested date that the transfer of calls, specified in the TC TO PRI field, is to be removed and the standard recorded announcement is to be provided.	N	8-8	CCYYMMDD CC – 00-99 YY – 00-99 MM – 01-12 DD – 01-31	<p>1. If populated and vv &lt;, = LSR.DDD, then return error: FTRPS112 TC PER MUST BE GREATER THAN DESIRED DUE DATE</p> <p>2. If populated and TC TO PRI is not populated, then return error: FTRPS113 TC PER IS PROHIBITED</p> <p>3. If populated and valid format not = CCYYMMDD, then return error: FTRPS114 TC PER VALID FORMAT = CCYYMMDD</p>	O
038 a	SDP - Shared Data Provider	Indicates the status of the shared data provider.	A	1-1	A= No current data provider exists B= Current data provider exists C= Change Wholesale Broadband with no change to CPE D= Remove Wholesale Broadband E= Add Wholesale Broadband F= Change Wholesale Broadband with change to CPE G= Add/Change to Optional Wholesale Broadband Features M= Migrate DSL to Wholesale Broadband	<p>1. If populated and vv = C, E, F, G and LNA = N, T, V, W, then return error: FTRPS115 SDP VALID VALUE C, E, F, G IS PROHIBITED</p> <p>2. If vv not = D and LNA = D and position 2 of LTOS = L, then return error: FTRPS116 SDP VALID VALUE = D</p> <p>3. If not populated and position 1 of LSR.REQTYP = D and LNA = N, V and the position 2 of LTOS = P or position 3 of LTOS = B or position 4 of LTOS = S, L, then return error: FTRPS117 SDP IS REQUIRED</p> <p>4. If populated and ((LNA = B, P, S, X) or (LNA = C and OTN is populated)), then return error: FTRPS118 SDP IS PROHIBITED</p> <p>5. If populated and IWJK is populated, then return error: FTRPS119 SDP IS PROHIBITED</p> <p>6. If populated and position 1 of LSR.REQTYP = D and (LNA does not = C, D, N, V and position 2 of LTOS not = L, P and position 3 of LTOS not = B and position 4 of LTOS not = S, L), then return error: FTRPS120 SDP IS PROHIBITED</p>	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>7. If populated and vv not = A, B, C, D, E, F, G, M, then return error: FTRPS121 SDP VALID VALUE = A, B, C, D, E, F, G, M</p> <p>8. If populated and LNA not = V and vv = M, then return error: FTRPS195 SDP VALUE OF M IS ONLY VALID WHEN LNA = V</p> <p>9.If not populated and LSR.REQTYP= DB, LSR.ACT=N,V, LSR.SLI=B,S and position 2 of LSR.TOS=P, return error FTRPS206 SDP REQUIRED</p> <p>10.If populated and vv does not = A and ISR is populated, return error FTRPS207 SDP VALID VALUE =A WHEN ISR IS POPULATED</p> <p>11.If populated and vv = B and LSR.REQTYP= DB, LSR.ACT=N, LSR.SLI=S and position 2 of LSR.TOS=P, then return error FTRPS208 SDP CANNOT = B</p> <p><b>Note:</b> Wholesale Broadband refers to the Wholesale Broadband product available across the Frontier footprint</p>	
038 b	LOOPQUAL - Loop Qualification Status	Indicates status of loop qualification process which is required for all premium loops.	A	1-1	C = Completed R = Required	<p>1. If populated and vv = R and SDP = C, E, F, then return error: FTRPS122 LOOPQUAL VALID VALUE = R IS PROHIBITED</p> <p>2. If not populated and ((SDP = A and position 2 of LTOS = P) or (SDP = E and LSR.TOS Position 3 not = B and LSR.TOS Position 4 not = S, L)), and NPA NXX is Acquired WV, then return error: FTRPS123 LOOPQUAL IS REQUIRED</p> <p>3. If populated and (SDP not = A, C, E, F and position 2 of LTOS not = P), then return error: FTRPS124 LOOPQUAL IS PROHIBITED</p> <p>4. If populated and vv not = C, R, then return error: FTRPS125 LOOPQUAL VALID VALUE = C, R</p>	O
038 c	ISR - Installation Service Requested	Identifies the functions to be performed by a technician doing DSL Premise service	AN	1-8	A= Synch Verification & Turn Up/Completion  B= Install 100 feet of Inside Wire or increment of  C= Install splitter at end-user premises	<p>1. If populated and vv does not contain A when vv contains B, C, D, E, F, H, J, then return error: FTRPS126 ISR MUST CONTAIN A WHEN B, C, D, E, F, H, J IS PRESENT</p> <p>2. If populated and vv contains more than one occurrence of A, C, E, F, H, J, then return error: FTRPS127 ISR VALID VALUE = A, C, E, F, H, J CAN ONLY OCCUR ONCE</p>	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
					D= Install Jack or Rewire existing Jack E= Install external modem (w/ software) F= Install internal modem (w/ software) H= Install microfilters J= PC configuration only <b>** Acquired WV Only:            B, C, D, E, F, H, J</b>	3. If populated and ((LNA not = N, V) or (position 2 of LTOS not = P) or (SDP not = A)), then return error: FTRPS128 ISR IS PROHIBITED  4. If populated and (dl > 30 or vv does not contain A, B, C, D, E, F, H, J), then return error: FTRPS129 ISR VALID VALUE = 1-30 A, B, C, D, E, F, H, J  5.If populated and vv = B, C, D, E, F, H, J and NPA NXX is not Acquired WV, return error FTRPS210 ISR INVALID FOR SERVICE TERRITORY	
039	JK CODE					<b>FRONTIER DOES NOT SUPPORT</b>	P
040	JK NUM					<b>FRONTIER DOES NOT SUPPORT</b>	P
041	JK POS					<b>FRONTIER DOES NOT SUPPORT</b>	P
042	JR					<b>FRONTIER DOES NOT SUPPORT</b>	P
043	NIDR - NID Request	Indicates a request for a new Network Interface Device (NID).	A	1	Y	1.If populated and vv does not =Y, return error FTRPS211 NIDR VALID VALUE =Y	O
044	IWJK - Inside Wire Jack Code	Indicates the standard code for the type of jack requested for inside wiring	AN	1-5		1.If populated and position 1 of LSR.REQTYP = D and LNA not = N, T, V, C, then return error: FTRPS130 IWJK IS PROHIBITED  2. If populated and dl > 5, then return error: FTRPS131 IWJK VALID LENGTH = 1-5  3.If not populated and IWJQ is populated, return error FTRPS212 IWJK IS REQUIRED WHEN IWJQ IS POPULATED  4.If populated and EU.STATE=CT, return error FTRPS204 IWJK PROHIBITED  <b>Note:</b> 1.Familiarization with the FCC's registration rules is requisite for all parties involved for the determination of the proper jack code for a given registered service. Registered jacks used to terminate category 1 and 3 services begin with the designation "RJ". 2.When multiple lines are terminating in one multi-line jack, the IWJK and IWJQ fields should only be populated for the first line. Jacks may be ordered on a line by line basis.	O
045	IWJQ - Inside Wire Jack Quantity	Indicates the number of jacks requested for inside wiring.	N	2-2	01-99	1. If not populated and IWJK is populated, then return error: FTRPS132 IWJQ IS REQUIRED	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>2. If populated and IWJK is not populated, then return error: FTRPS133 IWJQ IS PROHIBITED</p> <p>3. If populated and (dl &gt; 2 or dc not = numeric), then return error: FTRPS134 IWJQ VALID VALUE = 2 NUMERIC</p> <p>Note: When multiple lines are terminating in one multi-line jack, the IWJK and IWJQ fields should only be populated for the first line. Jacks may be ordered on a line by line basis.</p>	
046	IWT					<b>FRONTIER DOES NOT SUPPORT</b>	P
047	SYSTEM ID - System Identification	Identifies the customer's system to be used in a collocation arrangement	AN	1-5		<p>1. If populated and (dl &gt; 5 or dc not = alpha, numeric), then return error: FTRPS135 SYSTEM ID VALID VALUE = 1-5 ALPHA, NUMERIC</p> <p>2.If not populated and LSR.REQTYP = FB and LNA = N, V, return error FTRPS188 SYSTEM ID IS REQUIRED</p> <p>3. If populated and format not = AAANN, then return error: FTRPS189 SYSTEM ID VALID FORMAT = AAANN FOR FRONTIER</p> <p>Note: Applicable when the customer has assignment control in a collocation arrangement</p>	O
048	CABLE ID					<b>FRONTIER DOES NOT SUPPORT</b>	P
049	SHELF - Shelf	Identifies the number assigned to the customer's shelf to be used in a collocation arrangement.	<p>WV / Legacy: N</p> <p>F13: AN</p>	<p>WV / Legacy: 2-2 –</p> <p>F13: 2-6</p>		<p>1. If not populated and LNA = N, V and position 2 of LTOS = P and SDP = A, then return error: FTRPS137 SHELF IS REQUIRED</p> <p>2.If populated and dl does not = 2 or dc is not numeric and NPA NXX is not Frontier 13, return error FTRPS138 SHELF VALID VALUE = 2 NUMERIC</p> <p>3. If populated and dl &gt;6 or dc does not = alphanumeric and NPA NXX is Frontier 13, return error FTRPS213 SHELF VALID VALUE = 2-6 ALPHA NUMERIC</p> <p>Note: Prohibited for migrations from Line Split to Line Split.</p>	O
050	SLOT - Slot	Identifies the customer's specific connection slot to be used in a	AN /	WV / Legacy: 1-4		<p>1. If not populated and LNA = N, V and position 2 of LTOS = P and SDP = A, then return error: FTRPS139 SLOT IS REQUIRED</p>	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
		collocation arrangement		F13: 1-7		<p>2.If populated and dl &gt;4 or dc does not = alpha numeric and NPA NXX is not Frontier 13, return error FTRPS140 SLOT VALID VALUE = 1-4 ALPHA, NUMERIC</p> <p>3.If populated and dl&gt;7, dc is not alphanumeric and NPA NXX is Frontier 13, return error FTRPS214 SLOT INVALID VALUE</p> <p>Note: Prohibited for migrations from Line Split to Line Split.</p>	
051	SPORT					<b>FRONTIER DOES NOT SUPPORT</b>	P
052	RELAY RACK - Relay Rack	A code that identifies the customer's bay/cabinet in a central office and may also include the floor and aisle where the specific piece of equipment is located.	AN	1-10		<p>1. If populated and (dl &gt; 10 or dc not = alpha, numeric), then return error: FTRPS142 RELAY RACK VALID VALUE = 1-10 ALPHA, NUMERIC</p> <p>Note: The format and structure of this field is defined by Telcordia Technologies document BR 751-100-785. The Relay Rack consists of the following elements: 1. <b>Floor/Level</b> – Character positions one (1) and two (2) outline the Floor or Level value. This data element is a mnemonic code that consists of certain combinations of alpha, numeric and special characters. It defines a particular floor/level where frames are located. Valid entries are outlined in Telcordia Technologies document BR 751-100-785. (2 alphanumeric characters) 2. <b>Line-Up / Frame Function</b> – Character positions three (3) through seven (7) identify either a Line-Up or Frame Function. When this data element contains Line-Up data, it is a particular row of relay equipment in a central office. A Frame Function Code identifies the various frames, racks, bays and cabinets installed in a central office. Valid entries are outlined in Telcordia Technologies document BR 751-100-785. (1-5 alphanumeric characters) 3. <b>Bay Number</b> – Character positions eight (8) and nine (9) identify the Bay Number. This data element is a numeric code that identifies various bays or frames within a central office. Valid entries are outlined in Telcordia Technologies document BR 751-100-785. (2 numeric characters) 4. <b>Bay Designation</b> – Character position ten (10) identifies the Bay Designation. This data element is one (1) character that identifies the Front, Back or marker group of the switching system. Valid entries are outlined in Telcordia Technologies document BR 751-100-785. (1 alpha character)</p> <p>Note: Applicable when the customer has assignment control in a collocation arrangement.</p>	O
053	CHAN/PAIR - Channel/Pair	Identifies the specific channel or pair within the provider's cable to be used for connection	AN . - space	1-5		<p>1. If populated and (dl &gt; 5 or dc not = alpha, numeric, hyphen, period, space), then return error: FTRPS143 CHAN/PAIR VALID VALUE = 1-5 ALPHA, NUMERIC, HYPHEN, PERIOD, SPACE</p> <p>2.If populated and NPA NXX is Frontier 13 or EU.STATE=CT, return error FTRPS215 CHAN/PAIR PROHIBITED FOR SERVICE TERRITORY</p>	O
054	UNIT					<b>FRONTIER DOES NOT SUPPORT</b>	P



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
055	CFA - Connecting Facility Assignment	Identifies the provider carrier system and channel to be used.	A/N - space	1-42		<p>1. If not populated and LSR.ACT = C, N and position 2 of the LSR.TOS = Y, then return error: FTRPS144 CFA IS REQUIRED</p> <p>2. If populated and (LSR.ACT not = C, N or position 2 of the LSR.TOS not = Y), then return error: FTRPS145 CFA IS PROHIBITED</p> <p>3. If populated and (dl &gt; 42 or dc not = alpha, numeric, hyphen, period, space), then return error: FTRPS146 CFA VALID VALUE = 1-42 ALPHA, NUMERIC, HYPHEN, PERIOD, SPACE</p> <p><b>Format:</b> The Facility Identification consists of the following elements: 1.The Facility Designation which uniquely identifies a particular facility type between two terminal locations (variable length, 1 - 5 characters). 2.The Facility Type which is usually identified through the use of a code set found in the Telcordia Practice BR 795-450-100 (variable length, 1 - 6 characters). 3.The Channel/Pair number of the facility that is being used to provide the service shown (variable length, 1 - 5 characters). 4.The "A" Location, which is the location of the facility termination that has the lower alpha/numeric CLLI code. 5.The "Z" Location, which is the location of the facility termination that has the higher alpha/numeric CLLI code.</p>	O
056	CCEA					<b>FRONTIER DOES NOT SUPPORT</b>	P
057	SGNL					<b>FRONTIER DOES NOT SUPPORT</b>	P
058	SSIG - Start Signaling	Identifies the type of start signaling requested	A	2-2	GS = Groud Start <b>(REQTYP FB ONLY)</b>  LS=Loop start  WS=Wink start  DD=Delayed dial  IM=Immediate dial	<p>1. If populated and vv not = LS and LTOS = -P--, then return error: FTRPS147 SSIG VALID VALUE = LS</p> <p>2. If populated and vv not = GS, LS, WS, DD, IM, then return error: FTRPS149 SSIG VALID VALUE = GS, LS, WS, DD, IM</p> <p>3. If populated and vv = GS and position 1 of LSR.REQTYP = D, then return error: FTRPS194 SSIG VALID VALUE = GS IS PROHIBITED FOR REQTYT</p>	O
059	PULSE					<b>FRONTIER DOES NOT SUPPORT</b>	P
060	LSCP					<b>FRONTIER DOES NOT SUPPORT (FTRPS151)</b>	P
061	BA - Blocking Activity	Indicates the activity for the blocking of calls	A	1-1	A=Add  D=Delete  N=No change  E=Endstate  Z=Remove all blocking	<p>1. If populated and vv not = A and LNA = N, T, then return error: FTRPS155 BA VALID VALUE = A</p> <p>2. If populated and vv not = E and LNA = V and RL is populated, then return error: FTRPS156 BA VALID VALUE = E</p> <p>3.If not populated and LNA = N, T, V, return error FTRPS157 BA IS REQUIRED</p>	O





Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>4. If populated and SDP = C, D, E, F, G, then return error: FTRPS158 BA IS PROHIBITED</p> <p>5. If populated and LSR.ACT not = S, B and LNA not = N, T, V, C, then return error: FTRPS159 BA IS PROHIBITED</p> <p>6. If populated and vv not = A, D, N, E, Z, then return error: FTRPS160 BA VALID VALUE = A, D, N, E, Z</p> <p>7.If populated and vv = N and LNA = V, return error FTRPS193 BA=N PROHIBITED WHEN LNA=V</p>	
062	BLOCK - Block	Identifies the type of blocking on the telephone number	AN	1		<p>1. If not populated and BA = A, D, E, then return error: FTRPS161 BLOCK IS REQUIRED</p> <p>2. If populated and BA not = A, D, E, then return error: FTRPS162 BLOCK IS PROHIBITED</p> <p>3. If populated and (dl &gt; 1 or dc not alpha, numeric), then return error: FTRPS163 BLOCK VALID VALUE = 1 ALPHA, NUMERIC</p> <p>4.If populated and vv does not = 1 and position 3 of LSR.TOS = B or position 4 of LSR.TOS = S, return error FTRPS221 BLOCK VALID VALUE = 1</p> <p>5. If populated and vv is not = 1 and REQ TYP = DB and the 4th POS of LSR.TOS=V, then return error FTRPS231 BLOCK VALUE MAY ONLY BE 1 FOR WHOLESALE VOIP SERVICE</p> <p>Note: Block Matrices available by Service Territory from: <a href="http://frontier.com">Local References (frontier.com)</a> Block options vary by state and not all blocks are available in every Central Office</p> <p>To request no blocking, populate '1' in this field</p>	O
063	CC-ACT					<b>FRONTIER DOES NOT SUPPORT</b>	P
064	CC-NO					<b>FRONTIER DOES NOT SUPPORT</b>	P
065	CCT					<b>FRONTIER DOES NOT SUPPORT</b>	P
066	FLI					<b>FRONTIER DOES NOT SUPPORT</b>	P
067	DI					<b>FRONTIER DOES NOT SUPPORT</b>	P
068	CCDD					<b>FRONTIER DOES NOT SUPPORT</b>	P
069	CNAM					<b>FRONTIER DOES NOT SUPPORT</b>	P
069a	ODP – Office Dialing Plan					<b>FRONTIER DOES NOT SUPPORT (FTRPS165)</b>	P



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
070	BSPRAO					<b>FRONTIER DOES NOT SUPPORT</b>	P
071	FA - Feature Activity	Indicates the activity type for the feature.	A	1-1	N=Add/Install C=Change to feature detail D=Disconnect V= Conversion to new LSP as specified	<p>1. If populated and vv not = N, C, D and LSR.ACT = C and LSR.AC = B, C, D, E, then return error: FTRPS167 FA VALID VALUE = N, C, D</p> <p>2. If populated and vv not = N, C, D and LNA = C, then return error: FTRPS168 FA VALID VALUE = N, C, D WHEN LNA = C</p> <p>3. If populated and vv not = N and ((LNA = N, T) or (LNA = V and RL is populated)), then return error: FTRPS169 FA VALID VALUE = N</p> <p>4. If populated and vv not = N, V and LNA = V, then return error: FTRPS170 FA VALID VALUE = N, V WHEN LNA = V</p> <p>5. If populated and (LSR.ACT = S or LNA = B, D, P), then return error: FTRPS171 FA IS PROHIBITED</p> <p>6. If populated and vv not = N, C, D, V, then return error: FTRPS172 FA VALID VALUE = N, C, D, V</p> <p>7. If populated and the vv=C, V, N and LNA=X return error FTRPS216 FA=C, V, N PROHIBITED WHEN LNA=X</p> <p>8.If populated and vv=V and LNA=R, return error FTRPS217 FA=V PROHIBITED WHEN LNA=R</p> <p>9.If populated and vv=C and LNA=V, return error FTRPS218 FA=C PROHIBITED WHEN LNA=V</p> <p>10.If populated and LNA=B,Y,S, return error FTRPS219 FA PROHIBITED</p> <p>Note: Valid entry of "C" is only to be used when making a change to a feature detail (e.g., call forward to number, ring cycle, etc.). When requesting a line Service &amp; Equipment code change, two iterations of the FA and FEATURE fields must be provided; one iteration will have FA = D to remove the existing line Service &amp; Equipment code and the other iteration will have FA = N to add the new line Service &amp; Equipment code.</p>	O
072	FEATURE - Feature Codes	Identifies the type of feature associated with the line	AN + - # / *	1-6		1. If populated and FA is not populated, then return error: FTRPS173 FEATURE IS PROHIBITED	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						<p>2. If not populated and FA is populated, then return error: FTRPS174 FEATURE IS REQUIRED</p> <p>3. If populated and (dl &gt; 6 or dc not alpha, numeric, plus sign, hyphen, number sign, virgule, asterick), then return error: FTRPS175 FEATURE VALID VALUE 1-6 ALPHA, NUMERIC, PLUS SIGN, HYPHEN, NUMBER SIGN, VIRGULE, ASTERISK</p> <p>Note: 1.Valid Feature per CLEC contract or tariff 2.The Line Rate Service &amp; Equipment code is required with all TOS field values. The Line Rate Service &amp; Equipment code should be populated in the FEATURE field on the Resale, Port or Centrex forms. The Line Rate Service &amp; Equipment code must be valid for the end user's address/location to avoid any subsequent errors/rejects.</p>	
072 a	FEATQTY - Feature Quantity	Identifies the quantity associated with the FEATURE field	N	1-3	2-100	<p>1. If populated and (SDP not = E, F, G or FEATURE is not populated), then return error: FTRPS176 FEATQTY IS PROHIBITED</p> <p>2. If populated and (dl &gt; 3 or dc not = numeric), then return error: FTRPS177 FEATQTY VALID VALUE = 1-3 NUMERIC</p>	O
073	FEATURE DETAIL - Feature Detail	Identifies additional information for the type of feature associated with the line	AN & ' * : , \$ - # ( ) % . + " ; / space	1-200		<p>1. If not populated and FA = C, then return error: FTRPS178 FEATURE DETAIL IS REQUIRED</p> <p>2. If populated and FA not = C, N, V, then return error: FTRPS179 FEATURE DETAIL IS PROHIBITED</p> <p>3. If populated and (dl &gt; 200 or dc not alpha, numeric, ampersand, apostrophe, asterisk, colon, comma, dollar sign, hyphen, number sign, parentheses, percent sign, period, plus sign, quotation marks, semicolon, space, virgule, equal sign, then return error: FTRPS180 FEATURE DETAIL VALID VALUE = 1-200 ALPHA, NUMERIC, AMPERSAND, APOSTROPHE, ASTERISK, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PARENTHESES, PERCENT SIGN, PERIOD, PLUS SIGN, QUOTATION MARKS, SEMICOLON, SPACE, VIRGULE, EQUAL SIGN</p> <p>Note: 1.If ordering Fixed Call Forwarding or Call Forward Fixed-Busy/No Answer with UNE-P MWI, populate this field with the Voice Mail Access number. 2.Fixed Call Forwarding Service &amp; Equipment code requires 'TN=NPANXXXXXX' or 'TN=XNPANXXXXXX' in Feature Detail. 'X's' represent numeric values. If the Call Forward to TN is a long distance TN, a '1' must precede the 10 digit numeric Call Forward TN value.</p>	O



Fld Nbr	Field Name	Definition	Data Char	Field Length	Valid Values / Range of Values	Conditional Business Rules / Edits	R/O/P
						3. In some states, (i.e. California), "1" may precede the ten digit telephone number.	
074	REMARKS					<b>FRONTIER DOES NOT SUPPORT</b>	P

**APPENDIX A: ERROR MESSAGE TABLE**

Error Message Number	Error Message Text
FTRPS001	PQTY IS REQUIRED
FTRPS002	PQTY VALID VALUE = 1-5 NUMERIC
FTRPS003	PQTY VALID VALUE MUST EQUAL 1
FTRPS004	LOCNUM IS REQUIRED
FTRPS005	LOCNUM VALID VALUE = 1-3 NUMERIC
FTRPS006	LNUM IS REQUIRED
FTRPS007	LNUM VALID VALUE = 1-5 NUMERIC
FTRPS008	NPI IS REQUIRED
FTRPS009	NPI IS PROHIBITED
FTRPS010	NPI VALID VALUE = C, F WHEN NPDI = D
FTRPS011	NPI VALID VALUE = E, F WHEN NPDI = B
FTRPS012	WHEN LNA IS C AT LEAST ONE OF THE FIELDS FPI, PIC, LPIC, OTN, BLOCK, TSP, IWJK, FA MUST BE POPULATED OR SDP = D
FTRPS013	LNA VALID VALUE = N, T WHEN ACT=T
FTRPS014	LNA VALID VALUE = N WHEN ACT=C AND SDP=A
FTRPS015	ALL OCCURRENCES OF LNA MUST =V FOR ACT/LTOS COMBINATION
FTRPS016	LNA VALID VALUE = N, V, D
FTRPS017	LNA VALID VALUE = C, N, D, P, T, X, Z
FTRPS018	POS 4 PS.LTOS MUST = L WHEN POS 4 LSR.TOS=L
FTRPS019	LNA VALID VALUE = B WHEN ACT = B
FTRPS020	LNA VALID VALUE = S WHEN ACT = S
FTRPS021	LTOS MUST EQUAL --BS OR --BL
FTRPS022	LNA VALID VALUE = N WHEN ACT = N
FTRPS023	LNA VALID VALUE = T, N WHEN ONE OCCURRENCE = T AND ACT = C
FTRPS024	LNA VALID VALUE = V WHEN ACT = V
FTRPS025	LNA VALID VALUE = T IS PROHIBITED FOR ACTIVITY
FTRPS026	LNA VALID VALUE = Z ONLY WHEN ACT = C AND AC = A
FTRPS027	LNA IS PROHIBITED
FTRPS028	LNA IS REQUIRED
FTRPS029	LNA VALID VALUE = B, C, D, N, P, S, T, V, X, Z
FTRPS030	LTOS POSITION 2 INVALID
FTRPS031	LTOS POSITION 2 VALID VALUE = (-) HYPHEN,D, P, 1 WHEN POSITION 1 OF TOS = 2
FTRPS032	TC OPT VALID VALUE = N FOR THE STATE OF TX



Error Message Number	Error Message Text
FTRPS033	POS 4 PS.LTOS MUST = S WHEN POS 4 LSR.TOS=S
FTRPS034	LNA VALID VALUE = C, D, N, X WHEN ACT = M
FTRPS035	LTOS VALID VALUE = -1-R OR -D-R WHEN POSITION 4 OF TOS = R
FTRPS036	LTOS POSITION 1 VALID VALUE = HYPHEN
FTRPS037	LTOS POSITION 2 VALID VALUE = (-) HYPHEN,D, P, 1, 2, 3, 4, 5, 6
FTRPS038	LTOS POSITION 3 VALID VALUE = HYPHEN OR B
FTRPS039	LTOS POSITION 4 VALID VALUE = R, HYPHEN, S, L, V
FTRPS040	LTOS VALID LENGTH = 4
FTRPS041	TNS VALID VALUE = A IS PROHIBITED WHEN SDP = D
FTRPS042	TNS VALID VALUE = N IS PROHIBITED
FTRPS043	COIN OR PAL MUST BE ON STAND ALONE ACCOUNT
FTRPS044	RCF MUST BE ON STAND ALONE ACCOUNT
FTRPS045	TNS IS REQUIRED
FTRPS046	TNS IS PROHIBITED
FTRPS047	TNS VALID VALUE = A, N WHEN LENGTH = 1
FTRPS048	TNS VALID FORMAT = XXXXXXXXXXXX, XXXXXXXXXXXX-XXXX
FTRPS049	TNS VALID LENGTH = 1, 10, 15
FTRPS050	TERS VALID VALUE = 10 ALPHA, NUMERIC, HYPHEN, SPACE, COMMA, SEMICOLON
FTRPS051	
FTRPS052	INVALID LPIC
FTRPS053	RECCKT VALID DATA LENGTH = 1-41
FTRPS054	VPID NOT VALID FOR SERVICE TERRITORY
FTRPS055	LNA VALID VALUE – D, T WHEN DDDO IS POPULATED
FTRPS056	OTN IS REQUIRED
FTRPS057	OTN IS PROHIBITED
FTRPS058	OTN IS PROHIBITED
FTRPS059	OTN VALID VALUE = 10 NUMERIC
FTRPS060	EXKEY IS REQUIRED
FTRPS061	EXKEY VALID LENGTH = 1-6
FTRPS062	FPI VALID VALUE = R, S, T IS PROHIBITED
FTRPS063	FPI IS PROHIBITED
FTRPS064	FPI IS PROHIBITED
FTRPS065	FPI VALID VALUE = A, B, E, R, S, T
FTRPS066	PIC VALID VALUE = NC IS PROHIBITED
FTRPS067	PIC IS REQUIRED
FTRPS068	PIC IS PROHIBITED
FTRPS069	PIC IS PROHIBITED
FTRPS070	PIC VALID VALUE = NONE, NC, VOIP OR 2-4 NUMERIC
FTRPS071	LPIC VALID VALUE = NC IS PROHIBITED
FTRPS072	LPIC IS REQUIRED
FTRPS073	LPIC IS PROHIBITED



Error Message Number	Error Message Text
FTRPS074	LPIC IS PROHIBITED
FTRPS075	LPIC VALID VALUE = NONE, NC, VOIP OR 2-4 NUMERIC
FTRPS076	TSP IS PROHIBITED
FTRPS077	TSP IS PROHIBITED
FTRPS078	TSP VALID FORMAT = XXXXXXXXXX-XX
FTRPS079	SAN VALID VALUE = 1-30 ALPHA, NUMERIC, AMPERSAND, APOSTROPHE, ASTERISK, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PARENTHESES, PERIOD, QUOTATION MARKS, SPACE
FTRPS080	CKR VALID VALUE = 1-41 ALPHA, NUMERIC, AMPERSAND, APOSTROPHE, ASTERISK, PARENTHESES, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PERCENT, PLUS SIGN, QUOTE, SEMICOLON, SPACE, PERIOD
FTRPS081	ECCKT IS REQUIRED
FTRPS082	ECCKT VALID VALUE = 1-41 ALPHA, NUMERIC, VIRGULE
FTRPS083	RL IS REQUIRED
FTRPS084	RL IS PROHIBITED
FTRPS085	RL VALID VALUE = Y
FTRPS086	OECCKT IS REQUIRED
FTRPS087	OECCKT IS PROHIBITED
FTRPS088	OECCKT VALID VALUE = 1-41 ALPHA, NUMERIC, VIRGULE
FTRPS089	TC OPT IS REQUIRED
FTRPS090	TC OPT IS PROHIBITED
FTRPS091	LNA CANNOT = S WHEN LSR.TOS OR PS.LTOS =P
FTRPS092	
FTRPS093	TC OPT VALID VALUE = N, S, T
FTRPS094	TC TO PRI IS REQUIRED
FTRPS095	TC TO PRI IS PROHIBITED
FTRPS096	TC TO PRI VALID VALUE = 10 NUMERIC
FTRPS097	TCID IS REQUIRED
FTRPS098	TCID IS PROHIBITED
FTRPS099	TCID VALID VALUE FOR INITIAL OCCURRENCE = 1
FTRPS100	TC NAME IS REQUIRED
FTRPS101	TC NAME IS PROHIBITED
FTRPS102	TC NAME VALID VALUE = 1-35 ALPHA, NUMERIC, APOSTROPHE, COMMA, HYPHEN, PERIOD, SPACE
FTRPS103	TC TO SEC IS REQUIRED
FTRPS104	TC TO SEC IS PROHIBITED
FTRPS105	TC TO SEC VALID VALUE = 10 NUMERIC
FTRPS106	TCID 2 IS REQUIRED
FTRPS107	TCID 2 IS PROHIBITED
FTRPS108	TCID 2 VALID VALUE = 1-2 NUMERIC
FTRPS109	TCNAME 2 IS REQUIRED
FTRPS110	TCNAME 2 IS PROHIBITED
FTRPS111	TCNAME 2 VALID VALUE = 1-35 ALPHA, NUMERIC, APOSTROPHE, COMMA, HYPHEN, PERIOD, SPACE
FTRPS112	TC PER MUST BE GREATER THAN DESIRED DUE DATE



Error Message Number	Error Message Text
FTRPS113	TC PER IS PROHIBITED
FTRPS114	TC PER VALID FORMAT = CCYYMMDD
FTRPS115	SDP VALID VALUE C, E, F, G IS PROHIBITED
FTRPS116	SDP VALID VALUE = D
FTRPS117	SDP IS REQUIRED
FTRPS118	SDP IS PROHIBITED
FTRPS119	SDP IS PROHIBITED
FTRPS120	SDP IS PROHIBITED
FTRPS121	SDP VALID VALUE = A, B, C, D, E, F, G, M
FTRPS122	LOOPQUAL VALID VALUE = R IS PROHIBITED
FTRPS123	LOOPQUAL IS REQUIRED
FTRPS124	LOOPQUAL IS PROHIBITED
FTRPS125	LOOPQUAL VALID VALUE = C, R
FTRPS126	ISR MUST CONTAIN A WHEN B, C, D, E, F, H, J IS PRESENT
FTRPS127	ISR VALID VALUE = A, C, E, F, H, J CAN ONLY OCCUR ONCE
FTRPS128	ISR IS PROHIBITED
FTRPS129	ISR VALID VALUE = 1-30 A, B, C, D, E, F, H, J
FTRPS130	IWJK IS PROHIBITED
FTRPS131	IWJK VALID LENGTH = 1-5
FTRPS132	IWJQ IS REQUIRED
FTRPS133	IWJQ IS PROHIBITED
FTRPS134	IWJQ VALID VALUE = 2 NUMERIC
FTRPS135	SYSTEM ID VALID VALUE = 1-5 ALPHA, NUMERIC
FTRPS136	CABLE ID PROHIBITED
FTRPS137	SHELF IS REQUIRED
FTRPS138	SHELF VALID VALUE = 2 NUMERIC
FTRPS139	SLOT IS REQUIRED
FTRPS140	SLOT VALID VALUE = 1-4 ALPHA, NUMERIC
FTRPS141	LNA VALID VALUE = N WHEN ACT = N, T
FTRPS142	RELAY RACK VALID VALUE = 1-10 ALPHA, NUMERIC
FTRPS143	CHAN/PAIR VALID VALUE = 1-5 ALPHA, NUMERIC, HYPHEN, PERIOD, SPACE
FTRPS144	CFA IS REQUIRED
FTRPS145	CFA IS PROHIBITED
FTRPS146	CFA VALID VALUE = 1-42 ALPHA, NUMERIC, HYPHEN, PERIOD, SPACE
FTRPS147	SSIG VALID VALUE = LS
FTRPS148	LNA MUST = S WHEN ACT = S
FTRPS149	SSIG VALID VALUE = GS, LS, WS, DD, IM
FTRPS150	LNA CANNOT = N,D WHEN REQ TYP=DB, ACT=V AND POSITION 2 OF TOS=C
FTRPS151	LSCP IS NOT VALID FOR FRONTIER
FTRPS152	LNA CANNOT = D WHEN REQ TYP=DB ACT=V AND POSITION 2 OF LSR.TOS=P
FTRPS153	FULL ACCOUNT SUSPENSION REQUIRED



Error Message Number	Error Message Text
FTRPS154	LTOS POSITION 3 MUST = M WHEN POSITION 2 = P
FTRPS155	BA VALID VALUE = A
FTRPS156	BA VALID VALUE = E
FTRPS157	BA IS REQUIRED
FTRPS158	BA IS PROHIBITED
FTRPS159	BA IS PROHIBITED
FTRPS160	BA VALID VALUE = A, D, N, E, Z
FTRPS161	BLOCK IS REQUIRED
FTRPS162	BLOCK IS PROHIBITED
FTRPS163	BLOCK VALID VALUE = 1 ALPHA, NUMERIC
FTRPS164	LTOS MUST = LSR.TOS
FTRPS165	ODP IS PROHIBITED FOR FRONTIER
FTRPS166	TNS MUST BE DIFFERENT FROM OTN WHEN LNA=X
FTRPS167	FA VALID VALUE = N, C, D
FTRPS168	FA VALID VALUE = N, C, D WHEN LNA = C
FTRPS169	FA VALID VALUE = N
FTRPS170	FA VALID VALUE = N, V WHEN LNA = V
FTRPS171	FA IS PROHIBITED
FTRPS172	FA VALID VALUE = N, C, D, V
FTRPS173	FEATURE IS PROHIBITED
FTRPS174	FEATURE IS REQUIRED
FTRPS175	FEATURE VALID VALUE 1-6 ALPHA, NUMERIC, PLUS SIGN, HYPHEN, NUMBER SIGN, VIRGULE, ASTERISK
FTRPS176	FEATQTY IS PROHIBITED
FTRPS177	FEATQTY VALID VALUE = 1-3 NUMERIC
FTRPS178	FEATURE DETAIL IS REQUIRED
FTRPS179	FEATURE DETAIL IS PROHIBITED
FTRPS180	FEATURE DETAIL VALID VALUE = 1-200 ALPHA, NUMERIC, AMPERSAND, APOSTROPHE, ASTERISK, COLON, COMMA, DOLLAR SIGN, HYPHEN, NUMBER SIGN, PARENTHESES, PERCENT SIGN, PERIOD, PLUS SIGN, QUOTATION MARKS, SEMICOLON, SPACE, VIRGULE, EQUAL SIGN
FTRPS181	TSP VALID VALUE FOR POSITION 11 MUST = E, 0, 1, 2, 3, 4, 5
FTRPS182	TSP VALID VALUE FOR POSITION 12 MUST = 0, 1, 2, 3, 4, 5
FTRPS183	TCID 2 MUST BE SEQUENTIAL
FTRPS184	LNA VALID VALUE = C, N, D, P, X
FTRPS185	LNA VALID VALUE = N, V, D
FTRPS186	TNS REQUIRED WHEN REQTYP=DB AND ACT=C,V
FTRPS187	VPI NOT VALID FOR SERVICE TERRITORY
FTRPS188	SYSTEM ID IS REQUIRED
FTRPS189	SYSTEM ID VALID FORMAT = AAANN FOR FRONTIER
FTRPS190	LTOS REQUIRED
FTRPS191	PIC VALID VALUE = NONE
FTRPS192	LPIC VALID VALUE = NONE





Error Message Number	Error Message Text
FTRPS193	BA=N PROHIBITED WHEN LNA=V
FTRPS194	SSIG VALID VALUE = GS IS PROHIBITED FOR REQ TYP
FTRPS195	SDP VALUE OF M IS ONLY VALID WHEN LNA = V
FTRPS196	ONLY ONE TNS VALUE OF A IS ALLOWED
FTRPS197	VCI NOT VALID FOR SERVICE TERRITORY
FTRPS198	VPID2 NOT VALID FOR SERVICE TERRITORY
FTRPS199	VPI2 NOT VALID FOR SERVICE TERRITORY
FTRPS200	VC12 NOT VALID FOR SERVICE TERRITORY
FTRPS201	UDSPEED NOT VALID FOR SERVICE TERRITORY
FTRPS202	CBCID NOT VALID FOR SERVICE TERRITORY
FTRPS203	CBP1 NOT VALID FOR SERVICE TERRITORY
FTRPS204	IWJK PROHIBITED
FTRPS205	LTOS POSITION 2 INVALID
FTRPS206	SDP REQUIRED
FTRPS207	SDP VALID VALUE =A WHEN ISR IS POPULATED
FTRPS208	SDP CANNOT = B
FTRPS209	TCOPT VALID VALUE = N
FTRPS210	ISR INVALID FOR SERVICE TERRITORY
FTRPS211	NIDR VALID VALUE =Y
FTRPS212	IWJK IS REQUIRED WHEN IWJQ IS POPULATED
FTRPS213	SHELF VALID VALUE = 2-6 ALPHA NUMERIC
FTRPS214	SLOT INVALID VALUE
FTRPS215	CHAN/PAIR PROHIBITED FOR SERVICE TERRITORY
FTRPS216	FA=C, V, N PROHIBITED WHEN LNA=X
FTRPS217	FA=V PROHIBITED WHEN LNA=R
FTRPS218	FA=C PROHIBITED WHEN LNA=V
FTRPS219	FA PROHIBITED
FTRPS220	LTOS POSITION 1 VALID VALUE = 1, 2
FTRPS221	BLOCK VALID VALUE = 1
FTRPS222	LTOS POSITION 3 INVALID
FTRPS223	PIC 0000 INVALID
FTRPS224	LINE SPLIT MUST BE ON STAND ALONE ACCOUNT
FTRPS225	LTOS MUST EQUAL ---V
FTRPS226	PIC VALID VALUE MUST = VOIP
FTRPS227	LPIC VALID VALUE MUST = VOIP
FTRPS228	PIC VALUE INVALID
FTRPS229	LPIC VALUE INVALID
FTRPS230	POS 4 PS.LTOS MUST = V WHEN POS 4 LSR.TOS=V
FTRPS231	BLOCK VALUE MAY ONLY BE 1 FOR WHOLESALE VOIP SERVICE



**APPENDIX B - CHANGE CONTROL LOG**

DATE	FIELD	REVISION NUMBER	CHANGE
07/16/2021	All	October 2021 Release	Update version to 9.30.24
07/30/2021	TNS – 016	October 2021 Release	Change Rule: From: 2. If populated and vv = N and ((LNA not = C, N, X) or (position 2 of LSR.TOS not = D, E, J and position 4 of LSR.TOS not = F, R, W)) or EU.AAI does not = NEW ADDR, return error: FTRPS042 TNS VALID VALUE = N IS PROHIBITED To: 2. If populated and vv = N and ((LNA not = C, N, X) or (position 2 of LSR.TOS not = D, E, J, B and position 4 of LSR.TOS not = F, R,W,S) or EU.AAI does not = NEW ADDR, return error: FTRPS042 TNS VALID VALUE = N IS PROHIBITED
07/15/2022	All	October 2022 Release	Update version to 9.30.25
07/25/2022	LTOS – 013	October 2022 Release	Update Header – Add 4th Position 'V=VoIP' for all areas  Change Rule: From: 7. If populated and position 4 of vv not = R, hyphen, S, L and NPA NXX is not Frontier 13 or EU.STATE not = CT, then return error: FTRPS039 LTOS POSITION 4 VALID VALUE = R, HYPHEN, S, L To: 7. If populated and position 4 of vv not = R, hyphen, S, L, V and NPA NXX is not Frontier 13 or EU.STATE not = CT, then return error: FTRPS039 LTOS POSITION 4 VALID VALUE = R, HYPHEN, S, L, V  Add New Rules: 18.If populated and vv does not = ---V position 4 of LSR.TOS = V and NPA NXX is Acquired WV, return error FTRPS225 LTOS MUST EQUAL ---V 19. If populated and vv does not = V and position 4 LSR.TOS = V, then return error FTRPS230 POS 4 PS.LTOS MUST = V WHEN POS 4 LSR.TOS=V
07/25/2022	TNS – 016	October 2022 Release	Change Rule:  From: 2. If populated and vv = N and ((LNA not = C, N, X) or (position 2 of LSR.TOS not = D, E, J, B and position 4 of LSR.TOS not = F, R,W,S) or EU.AAI does not = NEW ADDR, return error: FTRPS042 TNS VALID VALUE = N IS PROHIBITED To: 2.If populated and vv = N and ((LNA not = C, N, X) or (position 2 of LSR.TOS not = D, E, J, B and position 4 of LSR.TOS not = F, R,W,S, V) or EU.AAI does not = NEW ADDR, return error: FTRPS042 TNS VALID VALUE = N IS PROHIBITED
07/25/2022	PIC – 022	October 2022 Release	Update Header – Add Valid Value VOIP  Change Rule: From: 5. If populated and vv not = NONE, NC and ((dl < 2 or > 4) or (dc not = numeric)), then return error: FTRPS070 PIC VALID VALUE = NONE, NC OR 2-4 NUMERIC To: 5.If populated and vv not = NONE, NC, VOIP and ((dl < 2 or > 4) or (dc not = numeric)), then return error: FTRPS070 PIC VALID VALUE = NONE, NC, VOIP OR 2-4 NUMERIC



DATE	FIELD	REVISION NUMBER	CHANGE
			<p>Add New Rules: 8.If populated and vv does not = VOIP and position 4 of LSR.TOS = V return error FTRPS226 PIC VALID VALUE MUST = VOIP 9. If populated and the vv = VOIP and the position 4 of LSR.TOS does not = V return error FTRPS228 PIC VALUE INVALID</p>
07/25/2022	LPIC – 023	October 2022 Release	<p>Update Header – Add Valid Value VOIP</p> <p>Change Rule: From: 5. If populated and vv not = NONE, NC and ((dl &lt; 2 or &gt; 4) or (dc not = numeric)), then return error: FTRPS075 LPIC VALID VALUE = NONE, NC OR 2-4 NUMERIC To: 5.If populated and vv not = NONE, NC, VOIP and ((dl &lt; 2 or &gt; 4) or (dc not = numeric)), then return error: FTRPS075 LPIC VALID VALUE = NONE, NC, VOIP OR 2-4 NUMERIC</p> <p>Add New Rules: 8.If populated and vv does not = VOIP and position 4 of LSR.TOS = V, return error FTRPS227 LPIC VALID VALUE MUST = VOIP 9. If populated and vv = VOIP and position 4 of LSR.TOS does not = V, return error FTRPS229 LPIC VALUE INVALID</p>
03/17/2023	All	June 2023 Release	Update version to 9.30.26
04/05/2023	LTOS – 013	June 2023 Release	<p>Update Header – Add Legacy 3<sup>rd</sup> Character Value F = Flat Rate</p> <p>Change Rule From: 15.If populated and position 3 of vv does not = B, P and NPA NXX is Legacy, return error FTRPS222 LTOS POSITION 3 INVALID To: 15.If populated and position 3 of vv does not = B, P, F and NPA NXX is Legacy, return error FTRPS222 LTOS POSITION 3 INVALID</p>
04/05/2023	BLOCK – 062	June 2023 Release	<p>Add New Rule: 5. If populated and vv is not = 1 and REQ TYP = DB and the 4th POS of LSR.TOS=V, then return error FTRPS231 BLOCK VALUE MAY ONLY BE 1 FOR WHOLESALE VOIP SERVICE</p>
7/12/2024	All	October 2024 Release	Update version to 9.30.28
07/24/2024	TC OPT-033	October 2024 Release	<p>Added Rule: 5. If populated and vv does not = N and the EU State = TX return error FTRPS032 TC OPT VALID VALUE = N FOR THE STATE OF TX</p>