



UNI DEMARC MOVES

Contents

Overview	2
Process	3
UNI Demarc Move (ACT = M or D/N)	4
EVC – UNI CKT ID REPOINT: EVCI = A	8
Change Log	10

Frontier Wholesale

Jurisdiction: All
Effective Date: 07/02/2018
Revised Date: 04/25/2023



UNI DEMARC MOVES

Overview

The purpose of this document is to provide guidance for a Demarc Move of a circuit on an existing Network Interface Device (NID).

If a move of the existing circuit is needed, please email Demarc.Move@FTR.com. Frontier will advise if the ASR(s) should be a Move or Disconnect/New Connect within 24 hours upon receipt of the email.

Note: Customer will need to give specific details of Move Locations using the SALI Form Location Designator (LD)/ Location Value (LV) and or Additional Address Information (AAI) and Remarks to provide specific details of requested move.



UNI DEMARC MOVES

Process

After the review is complete. Frontier will advise 'Next Step' for the DEMARC Move.

If ACT M is used for DEMARC Move, one ASR will be issued for the Request

1. UNI ASR order to Move DEMARC. RUID and NID (ESP CLLI) will remain the same. No order will be needed for EVC.
2. Frontier will strive to avoid any Network Interruptions, but interruptions may occur when Move is in progress.

If ACTs Disc/New are used for DEMARC Move, two ASRs will be issued for Requested Move.

Step 1: Combo UNI/EVC ASR ACT N will be issued with new Location information, utilizing LD/LV fields on the SALI Form. A New circuit and ESP may be assigned. RPON the ACT N and D ASR. Place Old CKT ID in Remarks.

Step 2: Combo UNI/EVC ASR ACT D will be issued to disconnect UNI/EVC Circuit from previous location. RPON the ACT D and N ASR.

(Note: If original install of UNI/EVC was not on a combo UNI/EVC order, then UNI and EVC must be issued on separate disconnect orders.)



UNI DEMARC MOVES

UNI Demarc Move (ACT = M or D/N)

ASR FORM - ADMINISTRATIVE		
FIELD	ENTRY	ASR Activity Type
CCNA	Populate what is existing currently on Circuit	N - Required D - Required M - Required
PON	Customers PON	N - Required D - Required M - Required
REQTYP	ED = End User	N - Required D - Required M - Required
ACT	N, D or M	N - Required D - Required M - Required
EXP	Populated if Expedite is requested Expedite not allowed when PNUM = FB%	N - Optional D - Optional M - Optional
RTR	F - Send FOC only S – Prohibited (when ACT = D, M) N - No response required	N - Required D - Required M - Required
SEI	Y	N - Required D - Required M - Required
QSA	01	N - Required D - Optional M - Required
PIU	100	N - Required D - Prohibited M - Required
BAN	E or Fully Populated Current BAN	N - Required D - Required M - Required
RPON	Place RPON on ACT N and D	N - Required D - Required M - Required
ECCKT	ECCKT of the UNI CKT ID	N - Prohibited D - Required M - Required
QTY	1	N - Required D - Required M - Required
TSP	Example: TSP12345C-E1 Required if existing on original Circuit	N - Required D - Required M - Required
SPEC	Populate what is existing currently on Circuit	N - Required D - Optional M - Required
ASC-EC	Prohibited	All Activities Prohibited
REMARKS	Populate Change associated with DEMARC Move	N - Optional D - Optional M – Optional **Recommended entry based on New Demarc Location



UNI DEMARC MOVES

ASR FORM BILLING		
FIELD	ENTRY	ASR Activity Type
ACNA	Populate what is existing currently on Circuit	N - Required D - Required M - Required
FUSF	Populate what is existing currently on Circuit	N - Required D - Prohibited M - Required
VTA	Populate what is existing currently on Circuit	N - Required D - Optional M - Required
PNUM	Populate what is existing currently on Circuit	N - Required D - Optional M - Required
ASR FORM CONTACT		
FIELD	ENTRY	ASR Activity Type
INIT	Example: Jane Smith	N - Required D - Required M - Required
INITIATOR TEL	Example: 9999999999	N - Required D - Required M - Required
INIT EMAIL	Example: Jane.Smith@abc.com	N - Optional D - Optional M - Optional
DSGCON	Example: Jane Smith	N - Required D - Prohibited M - Required
DSGCON TEL	Example: 9999999999	N - Required D - Prohibited M - Required
IMPCON	Example: Jane Smith	N - Required D - Required M - Required
IMPCON TEL	Example: Jane Smith	N - Required D - Required M - Required



UNI DEMARC MOVES

SES FORM – Switched Ethernet Services		
FIELD	ENTRY	ASR Activity Type
NC/NCI/SECNCI	Populate what is existing currently on Circuit	N - Required D - Required M - Required
ESP	11-character CLLI from original Circuit, this may change based on Activity taken for Move order	N - Optional D - Prohibited M - Required
GETO	W – Wire and bill Customer	N – Optional D - Prohibited M - Optional
SES FORM – Service Address Information		
FIELD	ENTRY	ASR Activity Type
PI	Y	N - Required D - Optional M - Required
EUNAME	End User's Name	N - Required D - Optional M - Required
SANO	Populate what is existing currently on Circuit	N - Conditional D - Optional M - Conditional
SASN	Populate what is existing currently on Circuit	N - Required D - Optional M - Required
SATH	Populate what is existing currently on Circuit	N - Required D - Optional M - Required
SASS	Populate what is existing currently on Circuit	N - Conditional D - Optional M - Conditional
LD1	Location Designation #1: Use to give New Designation of Demarc Location. Used on ACT N or M	N - Conditional D - Optional M – Conditional **Recommended entry based on New Demarc Location
LV1	Location Value #1: Use to give Designation Value of New Demarc Location. Used on ACT N or M	N - Conditional D - Optional M – Conditional **Recommended entry based on New Demarc Location



UNI DEMARC MOVES

FIELD	ENTRY	ASR Activity Type
LD2	Location Designation #2: Use to give New Designation of Demarc Location. Used on ACT N or M	N - Conditional D - Optional M – Conditional **Recommended entry based on New Demarc Location
LV2	Location Value #2: Use to give Designation Value of New Demarc Location. Used on ACT N or M	N - Conditional D - Optional M – Conditional **Recommended entry based on New Demarc Location
LD3	Location Designation #3: Use to give New Designation of Demarc Location. Used on ACT N or M	N - Conditional D - Optional M – Conditional **Recommended entry based on New Demarc Location
LV3	Location Value #3: Use to give Designation Value of New Demarc Location. Used on ACT N or M	N - Conditional D - Optional M – Conditional **Recommended entry based on New Demarc Location
AAI	Additional Address information: Use to give additional detail of where new Demarc is to be moved. Used on ACT N or M	N - Conditional D - Optional M – Conditional **Recommended entry based on New Demarc Location
CITY	Populate what is existing currently on Circuit	N - Required D - Optional M - Required
STATE	Populate what is existing currently on Circuit	N - Required D - Optional M - Required
JS	D	N - Required D - Optional M - Required
LCON	Identifies the local contact name for access	N - Required D - Optional M - Required
ACTEL	Identifies the telephone number to be used for the purpose of arranging access to the service address location for installation purposes	N - Required D - Optional M - Required
LCON_EMAIL	Identifies the electronic mail address of the local contact	N - Required D - Optional M - Required



UNI DEMARC MOVES

EVC – UNI CKT ID REPOINT: EVCI = A

ASR FORM - ADMINISTRATIVE	
FIELD	ENTRY
CCNA	Populate what is existing currently on Circuit
PON	Customers PON
REQTYP	SD
ACT	C
EXP	Populate if Expedite is requested based on contract agreements
RTR	F - Send FOC only N -No response required
EVCI	A (Will be prepopulated on PON when choosing Stand Alone EVC Service)
PIU	100
BAN	E or Fully Populated Current BAN
QTY	1
BILLING	
FIELD	ENTRY
ACNA	Populate what is existing currently on Circuit
VTA	Populate what is existing currently on Circuit
PNUM	Populate what is existing currently on Circuit
CONTACT	
FIELD	ENTRY
INIT	Example: Jane Smith
INITIATOR TEL	Example: 9999999999
INIT EMAIL	Example: Jane.Smith@abc.com
DSGCON	Example: Jane Smith
DSGCON TEL	Example: 9999999999
IMPCON	Example: Jane Smith
IMPCON TEL	Example: Jane Smith
EVC FORM ETHERNET VIRTUAL CONNECTION	
FIELD	ENTRY
EVCNUM	0001
NC	VLP-
EVCID	EVC Circuit ID
NUT	03
EVC FORM – ETHERNET VIRTUAL CONNECTION UNI MAPPING DETAIL [1]	
FIELD	ENTRY
UREF - 01	01
UACT	C
NCI	Populate existing NCI from existing RUID Circuit not changing
EVCSP	11-character CLLI Code from existing RUID Circuit not changing
RUID -1	Populate existing RUID Circuit not changing (Typically the NNI)



UNI DEMARC MOVES

EVC FORM – ETHERNET VIRTUAL CONNECTION LEVEL OF SERVICE MAPPING DETAIL

FIELD	ENTRY
LREF – 1	1
LOSACT	C
LOS	Populate the existing LOS existing on current RUID Circuit not changing (Populate only if not using SPEC field)
SPEC	Populate the existing SPEC CODE existing on current RUID Circuit not changing (Populate only if not using LOS field)
BDW	Populate the existing BDW value existing RUID Circuit not changing

EVC FORM – ETHERNET VIRTUAL CONNECTION UNI MAPPING DETAIL [2]

FIELD	ENTRY
UREF -02	02
UACT	N
NCI	Populate existing NCI code existing on current Circuit
EVCSP	Populate the “NEW” 11-character CLLI Code received on FOC from the NEW Connect UNI ASR.
RUID	Populate the “NEW” RUID Circuit ID received on FOC from the NEW Connect UNI ASR that is requesting the DEMARC Relocation

EVC FORM – ETHERNET VIRTUAL CONNECTION LEVEL OF SERVICE MAPPING DETAIL

FIELD	ENTRY
LREF - 01	1
LOSACT	N
LOS	Populate the existing LOS from original Circuit that is being disconnected (Populate only if not using SPEC field)
SPEC	Populate the existing product specific code from original Circuit that is being disconnect (Populate only if not using LOS field)
BDW	Populate the existing BDW from original Circuit that is being disconnect (Populate only if not using LOS field)

EVC FORM – ETHERNET VIRTUAL CONNECTION UNI MAPPING DETAIL [3]

FIELD	ENTRY
UREF -03	03
UACT	D
RUID	Populate UNI RUID being disconnected



UNI DEMARC MOVES

Change Log

Date	Page Number	Change
07/02/2018		Initial document
12/11/2018	3	Added Note for E-Path Process
07/10/2019	3	Added RPON requirement for ACT N & D
9/11/2019	3	Removed note about EPATH
6/18/2020	6	Added GETO
4/25/2023	3	Changed from 3 steps to 2 steps

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.