

# Local Interconnection Switched Access - Disconnect Trunks

#### REQTYP M, ACT D

#### VFO Product - Local Trunking Service

Revised: 05/25/2021

**Note:** Wireless Type 2A Trunks establish connections to the NXX prefixes served by end offices that subtend an Access Tandem connected to the Mobile Telephone Switching Office (MTSO). **Note:** Wireless Type 2B Trunks establish connections to NXX prefixes service by and end office connected directly to the Mobile Telephone Switching Office (MTSO).

### 001 - Access Service Request (ASR) Administrative Section

7101	71411111101141170 00011011		
Field	Description	Example	
CCNA	Customer Carrier Name Abbreviation	XXX (Identifies the IAC Code of the Carrier)	
PON	Purchase Order Number	Note: This Field is Controlled by Customer	
VER	Version Identification	Note: This Field is Controlled by Customer	
ICSC	Interexchange Customer Service Center	See Valid ICSC Entries https://wholesale.frontier.com/-	
		/media/WholesaleDocs/icsc-job-aid.ashx	
ACTI	Activity Indicator	D=Partial disconnect of trunk group	
		E=Disconnect trunks and re-route of traffic	
		F=Disconnect trunk group and no reroute of traffic	
CC	Company Code	Identifies the customer requesting local service	
DDD	Desired Due Date	Standard Interval	
REQTYP	Requisition Type and Status	M	
ACT	Activity	D	
AFO	Additional Forms	Populate with a Y for more than 24 trunks being requested.	
TQ	Translation Questionnaire Request	Required if ACTI = E	
LTP	Local Transport	Required	
CKR	Customer Circuit Reference	Customer Circuit ID	
QTY	Quantity	number of trunks being disconnected	
BAN	Billing Account Number	Entry of "E" for existing BAN	
ECCKT	Exchange Company Circuit ID	Circuit ID of trunks being disconnected	
ACTL	Access Customer Terminal Location	trunk ACTL CLLI	
RPON	Related Purchase Order Number	If necessary	
REMARKS	Remarks	Disconnect trunks and any other information you would like.	



#### **Bill Information**

Field	Description	Example
BILLNM	Billing Name	bill name for ACNA
SBILLNM	Secondary Billing Name	optional
ACNA	Access Customer Name Abbreviation	alpha
TE	Tax Exemption	alpha
FUSF	Federal Universal Service	E or N
	Fee	<b>Note:</b> Refer to the ASOG FUSF field Notes for Assessed or Exempted rules
STREET (Bill)	Street Address (BILL)	# and street name assigned by US Postal Service
FLOOR (Bill)	Floor (BILL)	optional
ROOM (Bill)	Room (BILL)	optional
CITY (Bill)	City (BILL)	city name for street address
STATE (Bill)	State/Province (BILL)	alpha
ZIP CODE (Bill)	Zip Code (BILL)	numerics
BILLCON	Billing Contact	employee from ACNA that can be contacted for billing issues
TEL NO (Bill)	Telephone Number (BILL)	numerics

#### **Contact Information**

Field	Description	Example
INIT	Initiator	customer's employee submitting ASR
TEL NO (INIT)	Telephone Number (Initiator)	numeric
INIT FAX NO	Initiator Facsimile Number	optional
INIT EMAIL	Initiator Electronic Mail Address	optional
DSGCON	Design/Engineering Contact	name of customer's designer
TEL NO (DSG CON)	Telephone Number (Design Contact)	numeric
DSG FAX NO	Design Facsimile Number	optional
STREET (DSG CON)	Street Address (Design Contact)	customer designer's mailing address street
FLOOR (DSG CON)	Floor (Design Contact)	optional
ROOM (DSG CON)	Room (Design Contact)	optional
CITY (DSG CON)	City (Design Contact)	customer designer's mailing address city
STATE (DSG CON)	State/Province (Design Contact)	alpha
ZIP CODE (DSG CON)	Zip Code (Design Contact)	numeric
DSG EMAIL	Design Electronic Mail Address	optional
IMPCON	Implementation Contact	customer's testing contact
TEL NO (IMP CON)	Telephone Number (Implementation	numeric
	Contact)	
D/TREC	Date and Time Received	mmddyy and hour, minute & AM or PM



#### 004 - Trunking Service Detail

Field	Description	Example
NC	Network Channel Code	NC code of existing trunks  Note: Customers must refer to iconectiv for accurate NC/NCI/SECNCI combinations or refer to the NC/NCI/SECNCI job aid found at
NCI	Network Channel Interface Code	See NC Note Abovehttps://wholesale.frontier.com/access- services/switched-access-ordering
SECLOC CFA TTT	Secondary Location Connecting Facility Assignment Transport Trunk Termination Code	end office or tandem CLLI ID of highest level facility numeric
QACI	Quantity Additional Circuit Information	Only required if more than 24 trunks requested
RECCKT	Related Exchange Company Circuit	DS1 to be disconnected if trunks and T1s to be disconnected
TCIC	Trunk Circuit Identification Code	required if SS7

## 019 - Translation Questionnaire (TQ) (Only used when ACTI=E) Common Section

Field	Description	Example
TECH CON	Customer Technical Contact (Translation)	customer's Translations tester
TEL NO (Tech Contact Translation)	Technical Contact Telephone Number (Translation)	numerics
TG ACT	Trunk Group Activity	D=Disconnect trunk group
TGTYP	Trunk Group Type	Required entry when disconnecting existing trunk group
TSC	Two Six Code	ACTI=E need to give new TSC traffic to be routed to when this group is disconnected
ALT REF	Alternate Routing Trunk Group Reference	Optional field entry when disconnecting a trunk group
REMARKS	Remarks	Communicate to the Routing Group the specifics of your order request.



**Interconnection Translation Routing** 

Field	Description	Example
TTEST TN	Translations Test Telephone Number (NPA/NXX)	585-123-4567
TECH CON	Customer Technical Contact (Translation)	John Smith
TEL NO (Tech	Technical Contact Telephone Number	585-555-6789
Contact	(Translation)	
Translation)		
TTEST RESP	Translations Test Response (NPA/NXX)	Milliwatt Tone
C.NPA/NXX (1)	Local Exchange Customer NPA/NXX	Input all codes that will be disconnected or rerouted from this trunk group. Use additional fields if needed

## 007 - Additional Circuit Information (ACI) Circuit Details

Field	Description	Example
REF NUM (1)	Reference Number	For every DS1 ordered, an ACI page must accompany the request.
CFA	Connecting Facility Assignment	1 0 1 / T 1 / 3 / ROCH
TRN	Trunk Number	Prohibited if TCIC is populated
HBAN	High Capacity Channel Billing Account Number	E
TCIC	Trunk Circuit Identification Code	Required if disconnecting SS7 trunks
RECCKT (1)	Related Exchange Company Circuit Identification	Populate T1 that is to be disconnected same time the trunks are being disconnected.
CKR	Customer Circuit Reference	Customer circuit ID



#### **Change Log:**

Date	Revision	
8/21/2015	Updated to add CTF (California, Texas and Florida) ICSC codes of GT10 and GT11 effective 4-1-2016	
05/25/2021	Update embedded URLs	

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBLITY OF SUCH DAMAGES.