

REQTYP M, ACT N

VFO Product Feature Group D

Revised: 06/07/2021

Note: Wireless Type 2A Trunks establish connections to the NXX prefixes served by end offices that subtend an Access Tandem connected to the Mobile Telephone Switching Office (MTSO).

Note: Wireless Type 2B Trunks establish connections to NXX prefixes service by and end office connected directly to the Mobile Telephone Switching Office (MTSO).

001 - Access Service Request (ASR)

Administrative Section

Field	Description	Example	
CCNA	Customer Carrier Name Abbreviation	XXX (Identifies the IAC Code of the Carrier)	
PON	Purchase Order Number	Note: This Field is Controlled by Customer	
VER	Version Identification	Note: This Field is Controlled by Customer	
ICSC	Interexchange Customer Service	See Valid ICSC Entries https://wholesale.frontier.com/-	
	Center	/media/WholesaleDocs/icsc-job-aid.ashx	
ACTI	Activity Indicator	C=New trunk group request	
D/TSENT	Date and Time Sent	System generated	
DDD	Desired Due Date	Standard Interval	
REQTYP	Requisition Type and Status	M=Trunking for Wireless	
ACT	Activity	N	
WST	Wireless Service Type	F=Type 2A	
		G=Type 2B	
LATA	Local Access Transport Area	Numeric	
RTR	Response Type Requested	F, N, or S	
AFO	Additional Forms	Populate with a Y for more than 24 trunks being requested.	
TQ	Translation Questionnaire Request	W=Wireless Translations	
		X=Wireless Translations and Code Translation Routing	
CUST	Customer Name	Company Name	
UNIT	Unit Identification	C	
PSL	Primary Service Location	Point of Interconnection CLLI	
PSLI	Primary Service Location Indicator	E=Lerg Switch CLLI is out of the LATA that the trunks are in. F=Lerg Switch CLLI within the same LATA as the trunks	
PIU	Percentage of Interstate Usage	Numeric	
LTP	Local Transport	Type 2A= LA when T1 rides T3 MF for standalone T1 Type 2B=	
	•	EA = when T1 rides T3 DF=standalone T1	
CKR	Customer Circuit Reference	Customer circuit ID	
QTY	Quantity	Number of Trunks being ordered	
BAN	Billing Account Number	Entry of "E" for existing BAN or N for new BAN	
ACTL	Access Customer Terminal Location	Trunk ACTL CLLI	
RPON	Related Purchase Order Number	If necessary	
REMARKS	Remarks	Install Type 2A/or 2B trunks and any other information you	
		would like.	
WST	Wireless Service Type	Required on all Land to Mobile or 2-way trunk groups	



Bill Information

Field	Description	Example
BILLNM	Billing Name	Bill name for ACNA
SBILLNM	Secondary Billing Name	optional
ACNA	Access Customer Name Abbreviation	alpha
FUSF	Federal Universal Service Fee	E or N
		Note: Refer to the ASOG FUSF field Notes for Assessed or Exempted rules
TE	Tax Exemption	alpha
STREET (Bill)	Street Address (BILL)	# and street name assigned by US Postal Service
FLOOR (Bill)	Floor (BILL)	optional
ROOM (Bill)	Room (BILL)	optional
CITY (Bill)	City (BILL)	city name for street address
STATE (Bill)	State/Province (BILL)	alpha
ZIP CODE (Bill)	Zip Code (BILL)	numeric
BILLCON	Billing Contact	employee from ACNA that can be contacted for billing
		issues
TEL NO (Bill)	Telephone Number (BILL)	numeric

Contact Information

Field	Description	Example
INIT	Initiator	customer's employee submitting ASR
TEL NO (INIT)	Telephone Number (Initiator)	numeric
INIT FAX NO	Initiator Facsimile Number	optional
INIT EMAIL	Initiator Electronic Mail Address	optional
DSGCON	Design/Engineering Contact	name of customer's designer
TEL NO (DSG CON)	Telephone Number (Design Contact)	numeric
DSG FAX NO	Design Facsimile Number	optional
STREET (DSG CON)	Street Address (Design Contact)	customer designer's mailing address street
FLOOR (DSG CON)	Floor (Design Contact)	optional
ROOM (DSG CON)	Room (Design Contact)	optional
CITY (DSG CON)	City (Design Contact)	customer designer's mailing address city
STATE (DSG CON)	State/Province (Design Contact)	customer designer's mailing address state
ZIP CODE (DSG CON)	Zip Code (Design Contact)	numeric
DSG EMAIL	Design Electronic Mail Address	optional
IMPCON	Implementation Contact	customer's testing contact



004 - Trunking Service Detail

Field	Description	Example	
NC	Network Channel Code	See following Note:	
		Note: Customers must refer to iconectiv for accurate NC/NCI/SECNCI	
		combinations or refer to the NC/NCI/SECNCI job aid found at	
		https://wholesale.frontier.com/access-services/switched-access-	
		ordering	
NCI	Network Channel Interface Code	See NC Note Above	
SECLOC	Secondary Location	Tandem or End Office CLLI Code	
CFA	Connecting Facility Assignment	ID of highest-level facility	
TTT	Transport Trunk Termination	9=Land to Mobile A=Mobile to Land 3=2Way	
	Code		
QACI	Quantity Additional Circuit	Only required if more than 24 trunks requested	
	Information		
TRFTYP	Traffic Type	OT-Originating TT = Terminating OT & TT for 2-way	
TCIC	Trunk Circuit Identification Code	Required when requesting SS7 trunks	
NC1	Network Channel Code (T1)	See NC Note Above	
SCFA	Secondary Connecting Facility	If CFA is populated with T3, the request for T1 required in this field	
	Assignment		
MUXLOC	Multiplexing Location	HUB CLLI	
CSL	Customer Switch Location	If ordering SS7 connectivity, place SS7 switch CLLI here	
CST	Customer Switch Type	If CSL is populated, this field is required	
CSPC	Customer Signaling Point Code	If ordering SS7 this field is required	
FACTL	Facility Access Customer	T1 ACTL CLLI Code	
	Terminal Location		

007 - Additional Circuit Information (ACI)

Circuit Details

Field	Description	Example
REF NUM (1)	Reference Number	For every DS1 ordered, an ACI page must accompany the request.
CFA	Connecting Facility Assignment	T3 or T1 the trunks are to ride
HBAN	High Capacity Channel Billing Account Number	E
TRN	Trunk Number	Prohibited if TCIC is populated
TCIC	Trunk Circuit Identification Code	Required if ordering SS7 trunks
SCFA	Secondary Connecting Facility Assignment	If T1 rides T3, then T1 is input in this field
CKR	Customer Circuit Reference	Customer Circuit ID



019 - Translation Questionnaire (TQ) Common Section

Field	Description	Example
TECH CON	Customer Technical Contact	customer's Translations tester
	(Translation)	
TEL NO (Tech Contact	Technical Contact Telephone	Numeric ex: 585-123-4567
Translation)	Number (Translation)	
TG ACT	Trunk Group Activity	N
TGTYP	Trunk Group Type	A
TSC	Two Six Code	AQ234567
APON	Associated Purchase Order Number	If associated with another PON.
GLARE	Glare Master	A
DIR	Directionality	10
TK SEQ	Trunk Group Hunt Sequence	LH
TK SIG	Trunk Signaling	TS
FACT	Feature Activity (ALT REF)	A
ALT REF	Alternate Routing Trunk Group	AQ234567
	Reference	
REMARKS	Remarks	Communicate to the Routing Group the specifics
		of your order request.

Interconnection Translation Routing

Field	Description	Example
TTEST TN	Translations Test Telephone Number (NPA/NXX)	585-234-5678
TECH CON	Customer Technical Contact (Translation)	J. R. Smith
TEL NO (Tech Contact Translation)	Technical Contact Telephone Number (Translation)	585-567-1234
TTEST RESP	Translations Test Response (NPA/NXX)	Milliwatt Tone
C.NPA/NXX (1)	Local Exchange Customer NPA/NXX	Input all codes that will be directed at this trunk group. Use additional fields if needed.

Testing Section

Field	Description	Example
TTEST TN	Translations Test Telephone Number (NPA/NXX)	585-123-4567
TTEST RESP	Translations Test Response (NPA/NXX)	Milliwatt Tone
ATTEST TN	Additional Translations Test Telephone Number	09723342112
ATTEST RESP	Additional Translations Test Response	Milliwatt Tone

This is an ASR Sample. There are other ASOG fields not included in this documentation. Please refer to ASOG for all field definitions. You may also reference Frontier's Custom Business rules at: https://wholesale.frontier.com/access-services/switched-access-ordering



Change Log:

Date	Revision
8/21/2015	Updated to add CTF (California, Texas and Florida) ICSC codes of GT10 and GT11 effective 4-1-2016
06/07/2021	Update embedded links

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBLITY OF SUCH DAMAGES.