



ATT Mobility Switched Ethernet Services Post Contract Execution Overview

Contents

Overview	2
ATTM New SPEC Codes for E-Path Services	3
Ineligible Embedded Base Circuits	4
Ineligible Embedded Base Circuit Ordering Guidelines (Where Circuit Retains Pre-Existing PNUM)4	
Use existing PNUM, UNI SPEC, VTA and EVC SPEC/LOS	4
Post-Conversion.....	5
Eligible Embedded Base UNI & EVC Circuit Ordering Guidelines and PNUM in AT&T Mobility system begins with SEAWWL or FLATFB	5
New Services UNI/EVC	6
New Services with New Tier Rate Structure PNUM EPAVW01999SCM792	6
New Activity & Eligible Embedded Base NNI	7
New Activity & Eligible Embedded Base Network to Network Interfaces (NNI) with New Tier Rate Structure PNUM SEW001NNIFLTRTE0.....	7
Change Log.....	8

Frontier Wholesale

Jurisdiction: All
Effective Date: 04/07/2022
Revised Date: 04/07/2022



Ethernet Services Post Contract Execution Overview

Overview

The purpose of the job aid is to assist with ASR submission for eligible embedded base circuits pre & post circuit conversion as outlined in the implementation & settlement agreements. Additionally, high level guidance has been included for the new E-Path Tier Rate Structure contract. This job aid was developed specifically for AT&T Mobility and should not be shared with or used by any other company.

Ineligible services are to stay on their current contract. Should AT&T want to add an ineligible circuit to the list of Eligible Embedded Base Services, a contract amendment will be required as outlined in the contract excerpt below.

Customer may elect to add switched ethernet CSBH circuits in-service with Frontier as of December 31, 2020, to Exhibit F by entering into an amendment with Frontier to add such circuits identified by Customer ("**Added Eligible Embedded Base Services**"). All Eligible Embedded Base Services, whether on the initial Exhibit F or added by amendment ("**Eligible Embedded Base Services**"), are subject to the limits and requirements of Section 8.1.3.1.2.

ASR Ordering Job Aids can be found at the following link:

<https://wholesale.frontier.com/access-services/att-mobility-job-aids>



Ethernet Services Post Contract Execution Overview

ATTM New SPEC Codes & PNUMs for E-Path Services

ENNI, UNI and EVC SPEC Codes shall be used as follows for all E-Path products:

Product	Circuit Type	ASR REQ TYP	SPEC	PNUM
E-Path	UNI - Primary	ED	EPATHU	EPAVW01999SCM792
	UNI - Secondary	ED	EPATHUS	EPAVW01999SCM792
	UNI – Temporary	ED	EPATHUT	EPAVW01999SCM792
	NNI	SD	EPATHN	SEW001NNIFLTRTE0
	EVC	SD	EPATHEP	EPAVW01999SCM792

*****Meetpoint*****

Meetpoint EVC ASRs will continue to use SPEC of OEMAR1 for E-Path



Ethernet Services Post Contract Execution Overview

Ineligible Embedded Base Circuits

Ineligible Embedded Base Circuit Ordering Guidelines (Where Circuit Retains Pre-Existing PNUM)

Use existing PNUM, UNI SPEC, VTA and EVC SPEC/LOS

Ethernet Virtual Connections (EVC)

C Activity (Change)

1. Bandwidth upgrades/downgrades
 - a. UNI has capacity for additional bandwidth
 - i. Permitted
 - b. UNI has No capacity
 - i. Not Permitted
 - ii. Amend contract to declare circuit as eligible
2. Re-Point to new NNI
 - a. Permitted
3. Telecom Service Priority (TSP)
 - a. Permitted

R Activity (Records)

1. Circuit Reference (CKR) changes
 - a. Permitted
2. VTA Changes
 - a. Not Permitted
3. Re-Terms under Pre-Existing PNUMs
 - a. Not Permitted

N Activity (New)

1. Not Permitted

User to Network Interface (UNI) and Network to Network Interfaces (NNI)

C Activity (Change)

1. Network Channel (NC) optional feature code changes (position 3 & 4)
 - a. Permitted
2. Telecom Service Priority (TSP)
 - a. Permitted
3. No capacity
 - a. Not Permitted
 - b. Amend contract to declare circuit as eligible

M Activity (Inside Move)

1. Permitted

R Activity (Records)

1. Circuit Reference (CKR) changes
 - a. Permitted
2. VTA Changes
 - a. Not Permitted
3. Re-Terms under Pre-Existing PNUMs
 - a. Not Permitted

N Activity (New)

1. Not Permitted



Ethernet Services Post Contract Execution Overview

Post-Conversion

Eligible Embedded Base UNI & EVC Circuit Ordering Guidelines and PNUM in AT&T Mobility system begins with SEAWAL or FLATFB	
When PNUM begins with SEAWAL or FLATFB	Primary UNI SPEC - EPATHU Additional UNI SPEC - EPATHUS Temp Site UNI SPEC - EPATHUT EVC SPEC - EPATHEP
Ethernet Virtual Connections (EVC)	
C Activity (Change)	1. Bandwidth upgrades/downgrades <ul style="list-style-type: none"> a. UNI has capacity for additional bandwidth <ul style="list-style-type: none"> i. Permitted b. UNI has No capacity <ul style="list-style-type: none"> i. Permitted ii. Follow 1G to 10G Process 2. Re-Point to new NNI <ul style="list-style-type: none"> a. Permitted 3. Telecom Service Priority (TSP) <ul style="list-style-type: none"> a. Permitted
R Activity (Records)	1. Circuit Reference (CKR) changes <ul style="list-style-type: none"> a. Permitted 2. VTA Changes <ul style="list-style-type: none"> a. Not Permitted 3. Re-Terms under Eligible Embedded Base PNUMs <ul style="list-style-type: none"> a. Not Permitted
N Activity (New)	1. Permitted only when adding an additional EVC to an existing UNI <ul style="list-style-type: none"> a. SPEC - EPATHEP b. NCI – (VLAN Based) - 02VLN.V, 02VLN.VP or 02VLN.VST
User to Network Interface (UNI)	
C Activity (Change)	1. Network Channel (NC) optional feature code changes (position 3 & 4) <ul style="list-style-type: none"> a. Permitted 2. Telecom Service Priority (TSP) <ul style="list-style-type: none"> a. Permitted 3. No capacity <ul style="list-style-type: none"> a. Not Permitted b. Follow 1G to 10G Process
M Activity (Inside Move)	1. Permitted
R Activity (Records)	1. Circuit Reference (CKR) changes <ul style="list-style-type: none"> a. Permitted 2. VTA Changes <ul style="list-style-type: none"> a. Not Permitted 3. Re-Terms under grandfathered PNUMs <ul style="list-style-type: none"> a. Not Permitted
N Activity (New)	1. Not Permitted



Ethernet Services Post Contract Execution Overview

New Services UNI/EVC

New Services with New Tier Rate Structure PNUM EPAVW01999SCM792	
Ethernet Virtual Connections (EVC)	
PNUM for All New Switched Ethernet Services	EPAVW01999SCM792
ACTIVITY Allowed	N, C, R, D
EVC NCI Codes	VLAN Based Reference AT&T Mobility <u>NC NCI SECNCI Codes - E-Path New Contract Job Aid</u>
EVC SPEC	EPATHEP If Meetpoint OEMAR1
VTA	60 If UNI is TEMP SITE (SPEC=EPATHUT) VTA must be MTM
User to Network Interface (UNI)	
PNUM for All New Switched Ethernet Services	EPAVW01999SCM792
ACTIVITY Allowed	N, C, R, M, D
UNI NC Codes	VLAN Based Reference AT&T Mobility <u>NC NCI SECNCI Codes -E-Path New Contract Job Aid</u>
SPEC CODES	Primary UNI SPEC - EPATHU Additional UNI SPEC - EPATHUS Temp Site UNI SPEC - EPATHUT
VTA	60 If UNI is TEMP SITE (SPEC=EPATHUT) VTA must be MTM
No Capacity on UNI	<ul style="list-style-type: none"> a. UNI has No capacity <ul style="list-style-type: none"> i. Follow 1G to 10G Process



Ethernet Services Post Contract Execution Overview

New Activity & Eligible Embedded Base NNI

New Activity & Eligible Embedded Base Network to Network Interfaces (NNI) with New Tier Rate Structure PNUM SEW001NNIFLTRTE0	
Network to Network Interfaces (NNI)	
PNUM for All New and Embedded Base NNI's	SEW001NNIFLTRTE0
ACTIVITY Allowed	N, C, R, M, D
NCI Codes	VLAN Based only Reference AT&T Mobility <u>NC NCI SECNCI Codes -E-Path New Contract Job Aid</u>
SPEC	EPATHN
VTA	60



Ethernet Services Post Contract Execution Overview

Change Log

Date	Page Number	Change
04/07/2022		Original Document

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.