



# Wireless Switched Access - Establish New Type 2A & 2B Trunks

## REQTYP M, ACT N

### VFO Product Feature Group D

Revised: 06/07/2021

**Note:** Wireless Type 2A Trunks establish connections to the NXX prefixes served by end offices that subtend an Access Tandem connected to the Mobile Telephone Switching Office (MTSO).

**Note:** Wireless Type 2B Trunks establish connections to NXX prefixes service by and end office connected directly to the Mobile Telephone Switching Office (MTSO).

### 001 - Access Service Request (ASR) Administrative Section

Field	Description	Example
CCNA	Customer Carrier Name Abbreviation	XXX (Identifies the IAC Code of the Carrier)
PON	Purchase Order Number	<b>Note:</b> This Field is Controlled by Customer
VER	Version Identification	<b>Note:</b> This Field is Controlled by Customer
ICSC	Interexchange Customer Service Center	See Valid ICSC Entries <a href="https://wholesale.frontier.com/dcaas-staticassets/wholesale/SourceFiles/Access/ICSC_Job_Aid.pdf">https://wholesale.frontier.com/dcaas-staticassets/wholesale/SourceFiles/Access/ICSC_Job_Aid.pdf</a>
ACTI	Activity Indicator	C=New trunk group request
D/TSENT	Date and Time Sent	System generated
DDD	Desired Due Date	Standard Interval
REQTYP	Requisition Type and Status	M=Trunking for Wireless
ACT	Activity	N
WST	Wireless Service Type	F=Type 2A G=Type 2B
LATA	Local Access Transport Area	Numeric
RTR	Response Type Requested	F, N, or S
AFO	Additional Forms	Populate with a Y for more than 24 trunks being requested.
TQ	Translation Questionnaire Request	W=Wireless Translations X=Wireless Translations and Code Translation Routing
CUST	Customer Name	Company Name
UNIT	Unit Identification	C
PSL	Primary Service Location	Point of Interconnection CLLI
PSLI	Primary Service Location Indicator	E=Lerg Switch CLLI is out of the LATA that the trunks are in. F=Lerg Switch CLLI within the same LATA as the trunks
PIU	Percentage of Interstate Usage	Numeric
LTP	Local Transport	Type 2A= LA when T1 rides T3 MF for standalone T1 Type 2B= EA = when T1 rides T3 DF=standalone T1
CKR	Customer Circuit Reference	Customer circuit ID
QTY	Quantity	Number of Trunks being ordered
BAN	Billing Account Number	Entry of "E" for existing BAN or N for new BAN
ACTL	Access Customer Terminal Location	Trunk ACTL CLLI
RPON	Related Purchase Order Number	If necessary
REMARKS	Remarks	Install Type 2A/or 2B trunks and any other information you would like.
WST	Wireless Service Type	Required on all Land to Mobile or 2-way trunk groups



# Wireless Switched Access - Establish New Type 2A & 2B Trunks

## Bill Information

Field	Description	Example
<b>BILLNM</b>	Billing Name	Bill name for ACNA
<b>SBILLNM</b>	Secondary Billing Name	optional
<b>ACNA</b>	Access Customer Name Abbreviation	alpha
<b>FUSF</b>	Federal Universal Service Fee	E or N <b>Note:</b> Refer to the ASOG FUSF field Notes for Assessed or Exempted rules
<b>TE</b>	Tax Exemption	alpha
<b>STREET (Bill)</b>	Street Address (BILL)	# and street name assigned by US Postal Service
<b>FLOOR (Bill)</b>	Floor (BILL)	optional
<b>ROOM (Bill)</b>	Room (BILL)	optional
<b>CITY (Bill)</b>	City (BILL)	city name for street address
<b>STATE (Bill)</b>	State/Province (BILL)	alpha
<b>ZIP CODE (Bill)</b>	Zip Code (BILL)	numeric
<b>BILLCON</b>	Billing Contact	employee from ACNA that can be contacted for billing issues
<b>TEL NO (Bill)</b>	Telephone Number (BILL)	numeric

## Contact Information

Field	Description	Example
<b>INIT</b>	Initiator	customer's employee submitting ASR
<b>TEL NO (INIT)</b>	Telephone Number (Initiator)	numeric
<b>INIT FAX NO</b>	Initiator Facsimile Number	optional
<b>INIT EMAIL</b>	Initiator Electronic Mail Address	optional
<b>DSGCON</b>	Design/Engineering Contact	name of customer's designer
<b>TEL NO (DSG CON)</b>	Telephone Number (Design Contact)	numeric
<b>DSG FAX NO</b>	Design Facsimile Number	optional
<b>STREET (DSG CON)</b>	Street Address (Design Contact)	customer designer's mailing address street
<b>FLOOR (DSG CON)</b>	Floor (Design Contact)	optional
<b>ROOM (DSG CON)</b>	Room (Design Contact)	optional
<b>CITY (DSG CON)</b>	City (Design Contact)	customer designer's mailing address city
<b>STATE (DSG CON)</b>	State/Province (Design Contact)	customer designer's mailing address state
<b>ZIP CODE (DSG CON)</b>	Zip Code (Design Contact)	numeric
<b>DSG EMAIL</b>	Design Electronic Mail Address	optional
<b>IMPCON</b>	Implementation Contact	customer's testing contact



# Wireless Switched Access - Establish New Type 2A & 2B Trunks

## 004 - Trunking Service Detail

Field	Description	Example
NC	Network Channel Code	See following Note: <b>Note:</b> Customers must refer to iconectiv for accurate NC/NCI/SECNCI combinations <b>or</b> refer to the NC/NCI/SECNCI job aid found at <a href="https://wholesale.frontier.com/resources/access-services/switched-access-ordering.html">https://wholesale.frontier.com/resources/access-services/switched-access-ordering.html</a>
NCI	Network Channel Interface Code	See NC Note Above
SECLOC	Secondary Location	Tandem or End Office CLLI Code
CFA	Connecting Facility Assignment	ID of highest-level facility
TTT	Transport Trunk Termination Code	9=Land to Mobile A=Mobile to Land 3=2Way
QACI	Quantity Additional Circuit Information	Only required if more than 24 trunks requested
TRFTYP	Traffic Type	OT-Originating TT = Terminating OT & TT for 2-way
TCIC	Trunk Circuit Identification Code	Required when requesting SS7 trunks
NC1	Network Channel Code (T1)	See NC Note Above
SCFA	Secondary Connecting Facility Assignment	If CFA is populated with T3, the request for T1 required in this field
MUXLOC	Multiplexing Location	HUB CLLI
CSL	Customer Switch Location	If ordering SS7 connectivity, place SS7 switch CLLI here
CST	Customer Switch Type	If CSL is populated, this field is required
CSPC	Customer Signaling Point Code	If ordering SS7 this field is required
FACTL	Facility Access Customer Terminal Location	T1 ACTL CLLI Code

## 007 - Additional Circuit Information (ACI) Circuit Details

Field	Description	Example
REF NUM (1)	Reference Number	For every DS1 ordered, an ACI page must accompany the request.
CFA	Connecting Facility Assignment	T3 or T1 the trunks are to ride
HBAN	High Capacity Channel Billing Account Number	E
TRN	Trunk Number	Prohibited if TCIC is populated
TCIC	Trunk Circuit Identification Code	Required if ordering SS7 trunks
SCFA	Secondary Connecting Facility Assignment	If T1 rides T3, then T1 is input in this field
CKR	Customer Circuit Reference	Customer Circuit ID



# Wireless Switched Access - Establish New Type 2A & 2B Trunks

## 019 - Translation Questionnaire (TQ) Common Section

Field	Description	Example
TECH CON	Customer Technical Contact (Translation)	customer's Translations tester
TEL NO (Tech Contact Translation)	Technical Contact Telephone Number (Translation)	Numeric ex: 585-123-4567
TG ACT	Trunk Group Activity	N
TGTYP	Trunk Group Type	A
TSC	Two Six Code	AQ234567
APON	Associated Purchase Order Number	If associated with another PON.
GLARE	Glare Master	A
DIR	Directionality	10
TK SEQ	Trunk Group Hunt Sequence	LH
TK SIG	Trunk Signaling	TS
FACT	Feature Activity (ALT REF)	A
ALT REF	Alternate Routing Trunk Group Reference	AQ234567
REMARKS	Remarks	Communicate to the Routing Group the specifics of your order request.

## Interconnection Translation Routing

Field	Description	Example
TTEST TN	Translations Test Telephone Number (NPA/NXX)	585-234-5678
TECH CON	Customer Technical Contact (Translation)	J. R. Smith
TEL NO (Tech Contact Translation)	Technical Contact Telephone Number (Translation)	585-567-1234
TTEST RESP	Translations Test Response (NPA/NXX)	Milliwatt Tone
C.NPA/NXX (1)	Local Exchange Customer NPA/NXX	Input all codes that will be directed at this trunk group. Use additional fields if needed.

## Testing Section

Field	Description	Example
TTEST TN	Translations Test Telephone Number (NPA/NXX)	585-123-4567
TTEST RESP	Translations Test Response (NPA/NXX)	Milliwatt Tone
ATTEST TN	Additional Translations Test Telephone Number	0 9 7 2 3 3 4 2 1 1 2
ATTEST RESP	Additional Translations Test Response	Milliwatt Tone

This is an ASR Sample. There are other ASOG fields not included in this documentation. Please refer to ASOG for all field definitions. You may also reference Frontier's Custom Business rules at: <https://wholesale.frontier.com/resources/reference-library/access-reference-documents.html>



# Wireless Switched Access - Establish New Type 2A & 2B Trunks

## Change Log:

Date	Revision
8/21/2015	Updated to add CTF (California, Texas and Florida) ICSC codes of GT10 and GT11 effective 4-1-2016
06/07/2021	Update embedded links

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.