



# Inside, Outside and Demarcation (NID) Moves

## Contents

Inside Moves .....	3
Outside Moves.....	6
Demarcation (NID) Moves.....	9
Full vs. Partial Move (when ACT T is not used) .....	10
Change Log .....	11

Frontier Wholesale

Jurisdiction: All  
Revised Date: 12/12/2018



## Inside, Outside and Demarcation (NID) Moves

### **Inside, Outside and Demarcation (NID) Moves**

The purpose of this document is to provide Wholesale Customer with descriptions and LSR ordering information for Inside, Outside and Demarcation Moves.



## Inside, Outside and Demarcation (NID) Moves

### Inside Moves

**Definition:** The move of a physical termination *within the same building*. The move may or may not require a dispatch to the customer premise to provision services. Inside moves do not allow for product changes.

**Supported REQYPES and LNAs (All Service Territories)**



## Inside, Outside and Demarcation (NID) Moves

Service Product	Order Scenario	REQTYP	ACT	LNA	Additional Considerations
Loop Service	Inside Move Physical Termination in Same Building	AB	M	M	
Loop Service	Inside Move Physical Termination in Same Building with New Install	AB	M	M, N	At least one LNA must be an M
Loop Service	Inside Move Physical Termination in Same Building with Change	AB	M	M, C	At least one LNA must be an M
Loop Service	Inside Move Physical Termination in Same Building with Disco	AB	M	M, D	At least one LNA must be an M
Wholesale Advantage	Inside Move Physical Termination in Same Building	DB	M	N	
Wholesale Advantage	Inside Move Physical Termination in Same Building with Change	DB	M	N, C	At least one LNA must be an N
Wholesale Advantage	Inside Move Physical Termination in Same Building with Disco	DB	M	N, D	At least one LNA must be an N
Wholesale Advantage	Inside Move Physical Termination in Same Building with Number Change	DB	M	N, X	At least one LNA must be an N
Resale	Inside Move Physical Termination in Same Building	EB	M	N	
Resale	Inside Move Physical Termination in Same Building with Change	EB	M	N, C	At least one LNA must be an N
Resale	Inside Move Physical Termination in Same Building with Disco	EB	M	N, D	At least one LNA must be an N
Resale	Inside Move Physical Termination in Same Building with Number Change	EB	M	X	
Resale Private Line	Inside Move Physical Termination in Same Building	KB	M	N	
Resale Private Line	Inside Move Physical Termination in Same Building with Change	KB	M	N, C	At least one LNA must be an N
Resale Private Line	Inside Move Physical Termination in Same Building with Disco	KB	M	N, D	At least one LNA must be an N
Resale Private Line	Inside Move Physical Termination in Same Building with Number Change	KB	M	X	At least one LNA must be an N



## Inside, Outside and Demarcation (NID) Moves

Service Product	Order Scenario	REQTYP	ACT	LNA	Additional Considerations
Resale Private Line	Inside Move Physical Termination in Same Building with New Install	KB	M	N	At least one LNA must be an N
DID/DOD/PBX	Inside Move Physical Termination in Same Building	NB	M	M	(TNA)
DID/DOD/PBX	Inside Move Physical Termination in Same Building with New Install	NB	M	M, N	At least one TNA must be an M
DID/DOD/PBX	Inside Move Physical Termination in Same Building with Change	NB	M	M, C	At least one TNA must be an M
DID/DOD/PBX	Inside Move Physical Termination in Same Building with Disco	NB	M	M, D	At least one TNA must be an M
DID/DOD/PBX	Inside Move Physical Termination in Same Building with Number Change	NB	M	X	At least one TNA must be an M
ISDN	Inside Move Physical Termination in Same Building	QB	M	N	
ISDN	Inside Move Physical Termination in Same Building with Change	QB	M	N, C	At least one LNA must be an N
ISDN	Inside Move Physical Termination in Same Building with Disco	QB	M	N, D	At least one LNA must be an N
ISDN	Inside Move Physical Termination in Same Building with Number Change	QB	M	X	At least one LNA must be an N



## Inside, Outside and Demarcation (NID) Moves

### Outside Moves

**Definition:** The move of a physical termination *at a new address*. The move may or may not require a dispatch to the customer premise to provision services. The End User may keep the same phone number should the new address reside in the same local serving wire center. The End User will be unable to keep the same phone number should the new address reside in a different local serving wire center. Outside moves allow for product changes.

#### Notes:

A RPON might be required to satisfy multiple line activities such partial outside move to a new service location while permanently retaining services at the current service location.

A partial outside move to a new service location while disconnecting services at the current location is accomplished on one PON.

- Every existing TN on the account must be populated in the EU DISCONNECTSECTION DISCNBR fields starting with the EATN as the first iteration; sections are added/copied and populated as needed.
- PONs that do not populated all existing TNs on the account in the DISCONNECTSECTION of the EU form will be rejected.
- Only TNs that are moving to the new service address are populated on the RS/PS TNS fields.
- TNs that are not populated on the RS/PS Form will be disconnected.
- Per Frontier business rules, a LNA of D, C or X is prohibited on an ACT of T.



## Inside, Outside and Demarcation (NID) Moves

### Supported REQTYPs and LNAs (Acquired WV / Legacy Service Territory)

Service Product	Order Scenario	REQTYP	ACT	LNA	Additional Considerations
Loop Service	Outside Move Physical Termination New Address	AB	T	N	
Loop Service	Outside Move Physical Termination New Address with New Install	AB	T	N	At least one LNA must be a N
Wholesale Advantage	Outside Move Physical Termination New Address	DB	T	N	
Wholesale Advantage	Outside Move Physical Termination New Address with New Install	DB	T	N	At least one LNA must be a N
Resale	Outside Move Physical Termination New Address	EB	T	N	
Resale	Outside Move Physical Termination New Address with New Install	EB	T	N	At least one LNA must be a N
Resale Private Line	Outside Move Physical Termination New Address	KB	T	N	
Resale Private Line	Outside Move Physical Termination New Address with New Install	KB	T	N	At least one LNA must be a N
DID/DOD/PBX	Outside Move Physical Termination New Address	NB	T	N	
DID/DOD/PBX	Outside Move Physical Termination New Address with New Install	NB	T	N	At least one LNA must be a N
Centrex	Outside Move Physical Termination New Address	PB	T	N	
Centrex	Outside Move Physical Termination New Address with New Install	PB	T	N	At least one LNA must be a N
ISDN	Outside Move Physical Termination New Address	QB	T	N	
ISDN	Outside Move Physical Termination New Address with New Install	QB	T	N	At least one LNA must be a N



## Inside, Outside and Demarcation (NID) Moves

### Supported REQTYPs and LNAs (**Connecticut / Frontier 13 Service Territory**)

Service Product	Order Scenario	REQTYP	ACT	LNA	Additional Considerations
Loop Service	Outside Move Physical Termination New Address	AB	T	N	
Loop Service	Outside Move Physical Termination New Address with New Install	AB	T	N	At least one LNA must be a N
Wholesale Advantage	Outside Move Physical Termination New Address	DB	T	T	
Wholesale Advantage	Outside Move Physical Termination New Address with New Install	DB	T	T, N	At least one LNA must be a T or N
Resale	Outside Move Physical Termination New Address	EB	T	T	
Resale	Outside Move Physical Termination New Address with New Install	EB	T	T, N	At least one LNA must be a T or N
Resale Private Line	Outside Move Physical Termination New Address	KB	T	N	
Resale Private Line	Outside Move Physical Termination New Address with New Install	KB	T	N	At least one LNA must be a N
DID/DOD/PBX	Outside Move Physical Termination New Address	NB	T	N	
DID/DOD/PBX	Outside Move Physical Termination New Address with New Install	NB	T	N	At least one LNA must be a N
Centrex	Outside Move Physical Termination New Address	PB	T	T	
Centrex	Outside Move Physical Termination New Address with New Install	PB	T	T, N	At least one LNA must be a T or N
ISDN	Outside Move Physical Termination New Address	QB	T	N	
ISDN	Outside Move Physical Termination New Address with New Install	QB	T	N	At least one LNA must be a N





## Inside, Outside and Demarcation (NID) Moves

### Demarcation (NID) Moves

**Definition:** A Network Interface Device (NID) is a point of interconnection between Frontier’s facilities and terminal equipment of protective apparatus or wiring at the CLEC/end user’s premises. The NID will be located on the CLEC/end user’s side of the Frontier protector or its equivalent at or near point of entry and is accessible to both Frontier and the CLEC. Only one (1) NID per dial tone line can be installed in a CLEC/end user’s premises. All inside wires, jacks, telephone(s), alarm, meter readings, or other terminal devices must be connected through the NID.

**Reasons to move a NID:** There are several reasons a CLEC will request to move a NID.

- Renovations to home or business
- Demolition of the building
- Construction where service exists

**Request Type:** The Request Type will depend on the type of service that is active at the end-user’s location. The Activity must equal C.

Request Type (REQTYP)	Activity
AB, BB, DB, EB, FB, KB, LB, QB, PB	C

**NIDR:** NIDR is a field found on the Service Specific Form for each request type (i.e. RS, PS, LS form, Etc.). The field must be populated as follows:

Request Type (REQTYP)	NIDR -Valid Entry	TOS Value
DB, EB, FB, KB, LB, QB	Y	2 <sup>nd</sup> character = 6
AB, BB	A = 2-Wire UNE NID B = 4-Wire UNE NID C = DS1 UNE NID	2 <sup>nd</sup> character = Z
PB	N/A	2 <sup>nd</sup> character = 6

*NOTE: The NIDR field is not supported on the Centrex Resale form (PB reqtype).*

**NID move charge:** The NID move request is charged the same as a field visit charge based on the time required to complete the work.



## Inside, Outside and Demarcation (NID) Moves

### Full vs. Partial Move (when ACT T is not used)

#### **FULL ACCOUNT MOVE**

**Description:** ACT T is an account level move. It is used when all lines at a location are disconnected at the time of the move. No lines remain at the existing location.

#### **LSR Ordering:**

**EU Form:** All account telephone numbers are identified in the disconnect section of the EU form.

**PS/RS Form:** The telephone numbers moving to the new location are identified in TNS fields on the service specific form. When an account telephone number is not among those identified as a moving number, it is disconnected.

#### **PARTIAL MOVE**

**Description:** When one or more lines moves to a new location and at least one line remains at the existing location, RPON activity is required to release the moving telephone number from the existing account so it may be installed at the new location.

#### **LSR Ordering:**

**RPON 1: ACT C LNA D** disconnects a moving telephone number from the existing account.

**Note:** When a moving number is a BTN, the ACT C PON must include account restructure direction:

- AC = A
- TNS = the telephone number that will become the new BTN
- LNA Z for each telephone number being restructured under the new BTN

**RPON 2: ACT N** installs the moving number at the new location



## Inside, Outside and Demarcation (NID) Moves

### Change Log

Date	Page Number	Change
12/15/16	7	Added PB reqtyp to the Demarcation (NID) Moves section on page 7
12/08/17	5, 6	Added Wholesale Advantage and Resale Order Scenario "Outside Move Physical Termination New Address with New Install" for Aquired WV/Legacy and Connecticut/Frontier 13 Service Territories
11/15/2018	3-6	Added REQTYPs KB/NB/QB order scenarios to inside and outside move sections. Removed LNA D, C and X from inside move scenarios. Added outside move notes surrounding need for RPON when retaining services and required LSR fields when disconnecting services on outside moves.
12/12/2018	8	Added Full vs. Partial Move (When ACT T is not used) information

DISCLAIMER: THIS DOCUMENTATION IS FOR INFORMATIONAL PURPOSES ONLY AND DOES NOT OBLIGATE FRONTIER TO PROVIDE SERVICES IN THE MANNER DESCRIBED IN THIS DOCUMENT. FRONTIER RESERVES THE RIGHT AS ITS SOLE OPTION TO MODIFY OR REVISE THE INFORMATION IN THIS DOCUMENT AT ANY TIME WITHOUT PRIOR NOTICE. IN NO EVENT SHALL FRONTIER OR ITS AGENTS, EMPLOYEES, DIRECTORS, OFFICERS, REPRESENTATIVES OR SUPPLIERS BE LIABLE UNDER CONTRACT, WARRANTY, TORT (INCLUDING BUT NOT LIMITED TO NEGLIGENCE OF FRONTIER), OR ANY OTHER LEGAL THEORY, FOR ANY DAMAGES ARISING FROM OR RELATING TO THIS DOCUMENT OR ITS CONTENTS, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.